Thank you for purchasing the Stereo Bluetooth Headset BTK-308, we hope you will enjoy all its benefits.

Please read this user's guide to get start, and to make the best usage of the neadset's many features.

# Driving safety

Keeping your eyes on the road, driving is your foremost responsibility. Obey traffic laws at all times: Make sure that using a Bluetooth wireless headset while driving is permitted by your local law.


# BEFORE USING YOUR HEADSET Betting to know your Stereo Bluetooth Headset

## Getting Started

To use your Bluetooth Stereo Headset, please follow these simple steps: Charge your headset

# Pair your headset with a Bluetooth-enabled mobile handset

Your headset overview



Fransferring a call/ Redial

KC Button: Increase Volume/Next song
K3 Button: Decrease Volume/Previous song
K2 Button &K3 Button: Multing the microphone
K1&K2 Button : Play / Pause / Stop music playing

# Charging the headset

Simply plug in provided USB cable to USB port then to USB Car Charger before using the headset for the first time. Your headset uses a rechargeable battery. You must charge the battery fully

full, the red indicator of the headset will turn off. Adaptor / Notebook Computer / Desktop Computer. Headset will start charging. The red indicator of headset will turn on when charging. When the battery is

Play the previous / next song Hold and press K2 Button for 2 seconds while music is on to play the next song. Hold and press K3 Button for 2 seconds while music is on to play the previous

Stop music playing
Hold and press K1 and K2 Button at the same time for 2 seconds to stop nusic playing

# Storage of the headset

- or in direct sunlight. (Storage at high temperatures can damage performance and reduces battery life).

  Do not expose the headset or any of its supplied parts to rain or other liquids. . Always store the headset with the power off and make sure it is safely protected . Avoid storage at high temperatures (above 60°C) such as in a hot vehicle

# roduct Specifications

Supported Bluetooth Profiles: Bluetooth Headset & Hands-free Profiles, A2DP Sluetooth Compliance: Bluetooth Version V2.1 +EDR, Class II

Operating Range: Up to 30 feet (10 meters) -requency: 2.40~2.48GHz

Falk Time: Up to 3~5 hours\*

Standby Time: Up to 70~100 hours\*

Battery Type: Rechargeable Lithium Polymer battery

Dimensions (L X W X T): 47.5 X 18.5 X 11.3 (mm)

Weight: 10.5 g (excluding accessories)

\*Depending on the phone type and usage, the actual time may vary.

# Correct disposal of this product

(Waste Electrical & Electronic Equipment)This marking shown on the product or its literature, indicates that it should not be disposed with other household wastes at the end of its working life.

their supplier and check the terms and conditions of the purchase contract. This product should not be mixed with other commercial wastes for disposal take this item for environmentally safe recycling. Business users should contact product, or their local government office, for details of where and how they can lousehold users should contact either the retailer where they purchased this and recycle it responsibly to promote the sustainable reuse of material resources incontrolled waste disposal, please separate this from other types of wastes To prevent possible harm to the environment or human health from

Bluetooth® is a trademark owned by Bluetooth SIG, Inc

Charge the headset until the red light on the headset turn off.
 The headset will be fully charged in approximately 1-2 hours.
 Remove the USB cable from the charging socket.

IMPORTANT: The headset cannot be used while charging



BASIC OPERATIONS
Iturning the headset on/off
1. To turn the headset on for about 3 seconds, the blue indicator of the headset flashes for 3 times. The headset is now turned on.

IMPORTANT: Once you turn on the headset again each time, there will be an auto-connecting between the headset and the mobile handset which is resumed. For pairing, please refer to "Pairing'. Depend on your phone type, the actual operation may vary.

. To turn the headset off Press and hold K1 Button for about 4 seconds, the red indicator flashes for 3 times, then off. The headset will be turned off.

When the blue indicator flashes red during standby mode, it means the headset is on low battery, please charge the headset.

Pairing will create a unique and enciphered wireless link between two Bluetooth enabled devices, such as your Bluetooth phone and Bluetooth headset.

1. Ensure that the headset is off (see "To turn the headset off section).

2. Press and hold the K1 Button for about 5 seconds until the indicator light

alternately flashes blue and red.

Set your Blueboth phone to discover the headset by following your phone's guide. Typically, the steps involve going to a "Setup". Connect, or "Blueboth menu on your phone and then selecting the option to discover Blueboth.

FCC Information
This device complies with Part 15 of the FCC rules Federal Communications Commission (FCC) Statement received; including interference that may cause undesired operation. cause harmful interference, and (2) this device must accept any interference Operation is subject to the following two conditions: (1) this device may not

equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may to provide reasonable protection against harmful interference in a residential This Equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC rules. These limits are designed

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user authority to

operate the equipment

Tested to comply with FCC standard. FOR HOME OR OFFICE USE

## Warning:

This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. & This device and its antenna(s) must not be coocated or conjunctior with any other antenna or transmitter

Your phone will find the "BTK-308" headset and ask if you want to pair with
it. Confirm this by pressing the "Yes" or "OK" key.
 Enter a passkey or PIN code "0000" (4 zeros), then press the "Yes" or "OK" key.

MPORTANT: If the pairing can't be completed within 60 seconds while the pairing mode is activated, that means the pairing is unsuccessfu please repeat Step 1 to Step 5 to pair the headset and the mobile phone again.

Making a call
Using the phone's keypad
1. Dial number on the keypad or select the contact name from the contact list
of your mobile phone.
2. Press phone's 'send/call' key.

## Voice Dialing

tag assigned for this feature. Please ensure your mobile phone supports voice dialing function and the voice

If your mobile support this function, shortly press K1 Button once. You'll then hear the voice-activation tone, say the name of the person you

Note: 1. For the mobile phone which don't support voice dialing function, shortly press the K1 button once will redial the last number; 2. Depend on your phone type, the actual operation may vary. Shortly press K1 Button to stop the voice dialing.

Ending a call

End a call from phone's keypad. press K1 Button once during a call.

# Answering a call

Press the K1 button briefly, when you receiving an incoming call.

Answer the call via your phone's keypad. You may then need to transfer the call to the headset by pressing the K1 Button for 2 seconds (depending on your phone setting)

# Last number redialing

the K1 button once will redial the last number; Shortly press K1 button twice to make the last number redial. For the mobile phone which don't support voice dialing function, shortly press

**Note:** Depend on your phone type, the actual operation may vary

# Rejecting an incoming call

Hold and press K1 for 2 seconds to reject a call

Adjusting the volume Press K3 Button to decrease Press K3 Button to decrease the volume level.

nelody, release it.

melody, release it. Phone to Headset: Press and hold K1 Button for 2 seconds when you hear Headset to phone: Press and hold K1 Button for 2 seconds when you hear Transferring a call

Note: For different mobile phone setting, you could only transfer a call by press the mobile phone's keypad. Depend on your phone type, the actual operation may vary.

# Muting the Microphone

You can put a call on hold by muting the microphone. To turn off the Muting Microphone: Press the K2 Button and K3 Button at the

To turn on the Muting Microphone: Press the K2 Button and K3 Button at the same time.There is a beep every 3 seconds.

# Additional Operations

Important: Below functions are only applicable to mobile handset with Bluelooth Handsfree Profile. Functionality varies depending on the mobile handset model you have. Please refer to your mobile handset user guide for additional information.

suiting with additional 3.5 mm jack earphone You can enjoy high quality stereo music by using this stereo Bluetooth headset



Play

Shortly press K1 and K2 Button at the same time while being connected to your Bluetooth audio device.

Shortly press K1 and K2 Button at the same time while the music is stopped. The music automatically comes back after you ended a call if you answered a call while listening to music

Shortly press K1 and K2 Button at the same time while listening to music Shortly press K1 and K2 Button at the same time again to listen to the song from the paused part -4-

# Stereo Bluetooth Headset User Manua **BTK-308**

