

**FCC ID: V5FDMR002**  
**FCC 1.1310**

Frequency MHz	Power dBm	Antenna		EIRP dBm	EIRP mW	Distance D cm	PD mW/m <sup>2</sup>	Limit mW/cm <sup>2</sup>	Margin dB
		Gain dBi	EIRP dBm						
1930	25.0	37	62.0	1584893	550	0.417	1	3.80	
1850	25.0	8	33.0	1995	20	0.397	1	4.01	
2110	25.0	37	62.0	1584893	550	0.417	1	3.80	
1710	25.0	5	30.0	1000	20	0.199	1	7.01	

PD=EIRP/(4πx<sup>2</sup>D<sup>2</sup>)

**IC: 11014A-DMR002**  
**HVIN: DMR419, DMR420**  
**CANADA RSS-102**

Frequency MHz	Power dBm	Antenna		EIRP dBm	EIRP W	Distance D m	PD W/m <sup>2</sup>	Limit W/m <sup>2</sup>	Margin dB
		Gain dBi	EIRP dBm						
1930	25.0	37	62.0	1585	5.5	4.17	4.61	0.43	
1850	25.0	8	33.0	2.00	0.2	3.97	4.48	0.52	
2110	25.0	37	62.0	1585	5.5	4.17	4.90	0.70	
1710	25.0	5	30.0	1.00	0.2	1.99	4.24	3.29	

PD=EIRP/(4πx<sup>2</sup>D<sup>2</sup>)