

## 01 Install the Mounting Plate

Place mounting plate in cutout in end panel. Align the plate with "TOP" pointing toward the top of the end panel.



## 02 Drill Mounting Holes

With the end panel on a flat, firm, and smooth surface, drill 3x holes into the end panel using **#3 drill bit**, using the holes in the mounting plate as a guide.



## 03 Affix the Mounting Plate

Place the three (3) M4 bolts through the mounting plate and affix using the three (3) M4 nuts. Tighten using a wrench and a drill.



## 04 Route the Cable Harness

Route the radio harness through the hole from the generator controller to the exterior.



## 05 Attach Radio Harness to Connectivity Accessory

05A

Align key with slot in connectors



05B

Press connectors together



05C

Tighten nut on radio harness



## 06 Attach Connectivity Accessory to End Panel

06A

Align the ARROW on the accessory with the ARROW on the mounting plate.



06B

Press the Accessory flush with the mounting plate.



06C

Turn the Accessory clockwise to attach



06D

A click will be heard when the accessory is fully installed

