

FCC ID: VHVBTVH2000

Operational Description of the equipment

Charging Battery

The Headset comes with a rechargeable battery included. The battery is not fully charged when it is new. For first time use, it takes 2 hours to fully charge the battery. Afterwards, it will take about 1.5 hours to fully charge the battery.
Plug the adapter into an AC outlet. The red indicator on the headset will turn on. When the battery is full, the red indicator will turn off.

Check the Headset buttons

S1 Button: Power on/off, Answer calls, End Call, Pairing, Voice Dial, Last Number Redial, Reject Call, Transfer Audio, Three Way Call
S2 Button: Volume Up, Mute
S3 Button: Volume Down, Mute

Turning the Headset On or Off

To turn the Headset on

Press and hold the S1 button for 3 seconds, then the blue indicator of the Headset flashes. The Headset is now turned on. (Note: When it is on low battery, the red indicator will flash.)

To turn the Headset off

Press and hold the S1 button for 3 seconds, then the Red indicator will flash, and then the Headset will turn off.

Product	Bluetooth Mono Headset
Model No.	VH-2000
Serial No.	VH-2xxx (x = 0~9 , A~Z)
Power Supply	DC 3.7 V , 0.02A
Frequency Band	2400-2483.5 MHz
Number of Channel	79
Channel Spacing	1 MHz
Rated RF Output Power	0 dBm
Modulation Type	GFSK , $\pi/4$ DQPSK , 8DPSK
Bit Rate of Transmission	2.1Mbp/s
Mode of Operation	Duplex.
Antenna Gain	2 dBi
Operating Temperature Range	-10 ~ 55 °C
Channel Bandwidth	1 MHz
Antenna Type	Ceramic Chip Antenna
Duty Cycle	50 %
Carrier Frequency	2402-2480 MHz