

Operational Description of the equipment

Getting Started

1. Charging Battery

The Headset comes with a rechargeable battery included. The battery is not fully charged when it is new. For first time use, it takes 3 hours to fully charge the battery. Afterwards, it will take about 2.5 hours to fully charge the battery. Plug the adapter into an AC outlet. The RED indicator on the headset will light on.(If the headset is power ON state, the RED LED will flash alternative with BLUE LED) When the battery is full, the RED indicator will turn off.

2. Turning the Headset On or Off

- To turn the Headset on

Turn the ON/OFF switch to ON position, then the blue indicator of the Headset flashes. The Headset is now turned on.

- To turn the Headset off

Turn the ON/OFF switch to OFF position, and then the Headset will turn off.

3. Pairing the Headset

You are required to pair the Headset with your Bluetooth mobile phone/audio device/PC/PDA before using the Headset.

Step 1 : Turn ON the headset. Hold and keep pressing the Pairing button for 6 seconds until the **blue** and the **red** indicators are flashing alternatively. The headset is now ready for pairing.

PRODUCT	Bluetooth Stereo Headset
MODEL NO.	VS-1000
POWER REQUIREMENTS	DC 3.7V, 0.05A
FREQUENCY BAND	2400 ~ 2483.5MHz
CARRIER FREQUENCY	2402~2480MHz
CARRIER FREQUENCY	CH0: 2402 MHz CH39: 2441 MHz CH78: 2480 MHz
NUMBER OF CHANNEL	79
CHANNEL SPACING	1MHz
RF OUTPUT POWER	0dBm
MODULATION TYPE	GFSK, II/4DQPSK, 8DPSK
DUTY CYCLE	50%
MODE OF OPERATION	Duplex
BIT RATE OF TRANSMISSION	2.1Mbps
ANTENNA TYPE	Ceramic Chip ANT
ANTENNA GAIN	4dBi
CHANNEL BANDWIDTH	1MHz
OPERATING TEMPERATURE	-10°C to 55°C