

## Operational Description of the equipment

### 1. Charging Battery

The Headset comes with a rechargeable battery included. The battery is not fully charged when it is new. For first time use, it takes 3 hours to fully charge the battery. Afterwards, it will take about 2 hours to fully charge the battery.

Plug the charge cable or adapter. The RED indicator on the headset will light on.(If the headset is power ON state, the RED LED will flash alternative with BLUE LED) when battery is charging.

When the battery is full, the RED indicator will turn off.

### 2. Turning the Headset On or Off

#### - To turn the Headset on

Turn the ON/OFF switch (S1) to ON position, then the blue indicator of the Headset flashes. The Headset is now turned on.

#### - To turn the Headset off

Turn the ON/OFF switch (S1) to OFF position, and then the Headset will turn off.

### 3. Pairing the Headset

You are required to pair the Headset with your Bluetooth mobile phone/audio device/PC/PDA before using the Headset.

Step 1 : Turn ON the headset. Hold and keep pressing the Pairing button (S2) for 3 seconds until the **blue** and the **red** indicators are flashing alternatively. The headset is now ready for pairing.

Step 2 : Initiate pairing process on your Bluetooth mobile phone/Audio Device/PC/PDA to pair with the Headset. After search, you can find the device name “VS-2000”

Step 3 : When asked the Passkey by the mobile phone, enter 1234 and confirm it. (*Note: The 1234 is a Default pin-code pre-stored in the Headset.*)

When pairing is successful, the red indicator will turn off and the blue indicator will flash..

If pairing can not finish in a period of time (approx. 2 minutes), the Headset will return to standby mode. You may need to repeat steps 1 to 3 until pairing succeeds.

### 4. Listening to Music

If the Bluetooth Device supported Bluetooth stereo audio (A2DP profile), you can listen music by the headset. And adjust the Headset volume by press the Volume Up (S3)and Volume Down (S6)button.

If the Bluetooth Device supported AVRCP profile also, you can control music playback by headset button PLAY (S2) / PAUSE (S2) / FWD (S4) / REV (S5)

### 5. SRS

Press and hold SRS button (S7) for 3 seconds to enable the SRS feature, and press and hold SRS button (S7) for 3 seconds to disable the SRS feature if SRS is enabled.

Press SRS button (S7) to select SRS mode when SRS is enabled. There are 4 SRS WOW HD mode in VS-2000.

## 6. Making Calls

### Using the phone keys to make call

Dial the number on the mobile phone as you normally do. Once the call has been set up, the sound will be transmitted to your Headset automatically.

## 7. Answering Calls and Ending Call

When the Headset is powered on, and there is an incoming call, you will hear a ring tone.

- (1) When the Headset rings, press the Answer button (S2) to answer.
- (2) Adjust the Headset volume by press the Volume Up (S3) and Volume Down (S6) button.
- (3) End calls by pressing End button (S2) or don't press any button.

## 8. Making Bluetooth Connection from Headset

By press the PLAY/PAUSE/Answer/End button (S2), the headset can connect with the paired stereo audio device (A2DP profile), like PC or MP3 player, automatically.

## Low Battery

When the **RED** indicator starts to flash and heard alert at headset, it indicates that the Headset is running low on battery.

Charge the Headset until the **RED** indicator turns off.

<b>Product</b>	Bluetooth Stereo Headset
<b>Model No.</b>	VS-2000
<b>Power Supply</b>	DC 3.7 V , 0.05A
<b>Frequency Band</b>	2400-2483.5 MHz
<b>Number of Channel</b>	79
<b>Channel Spacing</b>	1 MHz
<b>Rated RF Output Power</b>	0 dBm
<b>Modulation Type</b>	GFSK , II/4DQPSK , 8DPSK
<b>Bit Rate of Transmission</b>	2.1Mbp/s
<b>Mode of Operation</b>	Duplex.
<b>Antenna Gain</b>	2 dBi
<b>Operating Temperature Range</b>	-10 ~ 55 °C
<b>Channel Bandwidth</b>	1 MHz
<b>Antenna Type</b>	PCB Printing
<b>Duty Cycle</b>	50 %
<b>Carrier Frequency</b>	2402-2480 MHz