



<p>Thank you for purchasing the Yada Winplus Bluetooth® headset. The latest wireless technology product from Winplus. We hope you will enjoy all the features and benefits offered by the YD-V4 Headset. These features and benefits were designed with the goal of making wireless communication more convenient for the user.</p> <p>Winplus USA 820 South Wanamaker Avenue, Ontario, CA 91764 customercare@winplususa.com www.winplususa.com</p> <p>Winplus Europe Unit 4, Two Counties Estate, Falconer Road, Haverhill, Suffolk CB9 7XZ, UK. info@winplus-europe.com www.winplus.net</p> <p>Winplus Asia Sulite 6-11, 7th Floor, Corporation Park, 11 On Lai Street, Sha Tin, N.T., Hong Kong info@winplus.net www.winplus.net</p>	<p style="text-align: center;">CONTENTS</p> <p style="text-align: center;">DISCLAIMER WARRANTY / LIABILITIES PACKAGE CONTENT BATTERY OPERATIONS HEADSET OPERATION VOICE OVER INTERNET PROTOCOL (VOIP) APPLICATION CUSTOMER SERVICE / CONTACT US PAGE FCC/ICC</p> <p>YD-V4 Headset Specifications:</p> <ul style="list-style-type: none"> Bluetooth® Spec.: v2.1 + EDR Class 2 Bluetooth® Frequency: 2.402 GHz - 2.480 GHz, 2.4G ISM Band Standby Time: 120 Hours Talk Time: 5 Hours Standby Time: 120 Hours Profiles supported: HSP, HFP Frequency Range: 2.402 GHz - 2.480 GHz, 2.4G ISM Band Operating Range: 10 Meters Pairing: up to 7 devices Rechargeable Lithium Ion Battery Charger Adapter Output: DC 5V, 200mA Operating Temperature: 0°C to 35°C Storage Temperature: -20°C to 80°C
--	---

1 2

DISCLAIMER

- Distracted driving is dangerous. Always use the Bluetooth® Device in a manner that does not reduce your attention and ability to drive carefully and safely.
- Adhere to all applicable traffic laws and motor vehicle regulations applicable to the device.
- Consult local laws and regulations for any restrictions on installation or use. Do not install on an open airbag. Such installation could interfere with airbag deployment or could cause the product or another object to become a projectile, which could injure or kill you or others.
- Ensure the product location will not obstruct your vision while driving.
- Turn off the headset prior to using an airbag or other safety device.
- Small parts may be a choking hazard. Do not allow children to play with the headset.
- Observe all signs that require an electrical device to be switched off in designated areas. These may include hospitals, blasting areas or potentially explosive atmospheres.

WARRANTY / LIABILITIES

LIMITED WARRANTY

WINPLUS NORTH AMERICA
WINPLUS North America warrants, to the original purchaser, that its products are free from defects in material and workmanship for 1 year from the date of original purchase. Where permitted by law, WINPLUS North America's liability shall be limited to that set forth in this limited express warranty. This limited express warranty shall be the exclusive remedy of the purchaser and WINPLUS North America makes no other warranty of any kind aside from the limited express warranty stated above.

Note: Warranty only applies for North America customers or purchases made in the North America.

3 4

2. If it is necessary to return your product for service, please return it securely packed, preferably in the original shipping box, and freight and insurance prepaid to the following address:
ATTN: WINPLUS BLUETOOTH PRODUCTS RETURNS
820 South Wanamaker Avenue,
Ontario, CA 91764

3. Please include a detailed explanation of the problem you are having.
4. If your product is found by WINPLUS North America to have a defect in material or workmanship, within the warranty period, it will be repaired or replaced at no charge and returned to you prepaid.

WINPLUS North America makes no other warranty of any kind aside from the limited express warranty stated herein.

DISCLAIMER OF WARRANTIES, INCLUDING WARRANTY OF MERCHANTABILITY AND WARRANTY OF FITNESS FOR PARTICULAR PURPOSE: EXCEPT AS SPECIFICALLY SET FORTH HEREIN, NO WARRANTY OR REPRESENTATION, EXPRESS OR IMPLIED, IS MADE AS TO THE YD-V4 BLUETOOTH® HEADSET. EXCEPT AS EXPRESSLY SET FORTH HEREIN, WINPLUS NORTH AMERICA AND/OR ITS AFFILIATES EXPRESSLY DISCLAIMS, WITHOUT LIMITATION, ANY STATUTORY WARRANTIES AND ALL IMPLIED WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.

WINPLUS North America and/or its affiliates are not responsible for a user's intended or actual use of the YD-V4 Bluetooth® Headset. In no event shall WINPLUS North America and/or its affiliates have any liability for any losses (whether direct or indirect, in contract, tort or otherwise) incurred in connection with the YD-V4 Bluetooth® Headset. Neither shall WINPLUS North America and/or its affiliates have any liability for any decision, action or inaction taken by any person in reliance on the YD-V4 Bluetooth® Headset, or for any delays, inaccuracies and/or errors in connection with the YD-V4 Bluetooth® Headset and its functioning.

5 6

WINPLUS AUSTRALIA / HONG KONG

LIMITED WARRANTY

This Yoda product is warranted against faulty workmanship for a period of 2 years from date of purchase. Liability is limited to replacement of the product and claims for associated or consequential loss or damage will not be accepted. Warranty is void and does not apply if the product has been damaged or rendered faulty by accident, abuse, misuse, incorrect application or if the product has been modified or tampered with. Proof of purchase is required to validate warranty claims. If this product is faulty, simply return it to the place of purchase with your receipt for a replacement product. No refunds or credits will be issued. Replacement is limited to a Yoda product of the same or similar model.

PACKAGE CONTENT

7 8

BATTERY OPERATIONS

IMPORTANT: The Bluetooth® headset comes pre-charged, but it is recommended to charge the battery until the solid red light turns off before using for the first time. Amount of time will be depend on current charge level of battery.

Charging the YD-V4 Bluetooth® headset using 12V/24V direct charger.

The YD-V4 Direct Charger can be adjusted to fit any 12V power port. Make sure to press the **Lock Button** to adjust.

- Plug 12V/24V direct charger into the vehicle cigarette lighter socket
- Place Bluetooth® headset in the direct charger

NOTE: Make sure the On/Off Switch of the Direct Charger is on the "On" position for it to charge the YD-V4.

- Verify LED shows a steady red light, indicating device is charging
- Headset will only charge while vehicle ignition is in the "ON" or "ACC" position. Do not leave the ignition in either of these positions while not driving
- Device LED red light turns off once the battery is fully charged

9 10

HEADSET OPERATION

Power On/Off
To turn headset On:

- Press and hold **S1** until LED light turns blue
- Low tone followed by a high tone indicates that the YD-V4 is powered up
- Blue LED will flash every 3 seconds

Auto On
Headset will automatically power on when placed into the direct charger

NOTE: Auto On feature only works when headset is actively charging

11 12

To turn headset Off:

- Press and hold **S1** until LED light turns red
- Listen for a high tone followed by a low tone will indicate that the YD-V4 is powered down

Auto Off
Headset will automatically power off after 5 minutes if

- No Bluetooth® connection is detected and
- Headset is not connected to charging

IMPORTANT: Headset will not power off after 5 minutes when recharging the battery.

Headset Pairing/Linking

Pairing Bluetooth® enabled devices like mobile phones and headsets authorizes the devices to work with each other and only needs to be performed once. Headset can be paired with up to 7 devices. Only 1 device can be used at a time. (Maximum 2 in Two-Link Mode)

Before Pairing the YD-V4 headset:

- Ensure the Bluetooth® on your mobile phone is activated
- Ensure that you have read the pairing steps in your user manual
- Ensure the headset is fully charged
- Direct charger is disconnected
- The headset is turned off

13 14

If the mobile phone failed to detect the YD-V4 and did not successfully pair,

- Turn the headset and phone off, wait for 10 seconds
- Turn phone power on
- Repeat the pairing instructions from the beginning

Re-Establishing Bluetooth® Link:

You will need to re-establish a link between the YD-V4 Bluetooth® headset and your mobile phone before you can make or receive any calls. Follow instructions provided by your mobile phone to ensure you can establish a successful link. If you do not have your mobile phone operating instructions available, follow the typical steps below:

- Depending on your mobile phone, the link will either be established automatically and the LED status should have a blue light flashing every 3 seconds indicating the device was linked successfully
- Other mobile phones will give you a prompt to accept the link request from the YD-V4 before establishing a link, select Yes or OK, if you get a prompt

15 16

CAUTION: Some phones put the Bluetooth® connection into Standby Mode if it has not been used for some time. If an incoming call is received, only the mobile phone will ring. It could take a few seconds (2-3 ring tones) before the call is transferred to the headset. Wait until the ring is heard on the headset before taking the call. Do not press S1 before the call is transferred to the headset to avoid conflict with the mobile phone.

Transferring the Calls

The YD-V4 is capable of transferring calls from your mobile phone to YD-V4 headset or vice versa. Follow your mobile phone operating instructions for transferring call to ensure successful transfer of calls between the YD-V4 headset and your mobile phone. If instructions are not available, use the typical instructions below to transfer your calls.

- When in session, press and hold **S1** for 3 seconds to transfer the call from your mobile phone headset to the YD-V4 headset or vice versa

Rejecting an incoming call

To reject a call:

- Press and hold **S1** until you hear 2 tones while headset is ringing
- Call should be dropped once tone 2 is heard

NOTE: This feature works on mobile phones with the "Handsfree" profiles only

17 18

Outgoing Calls

- Manual
- Voice Activated
- Redial

To make outgoing calls manually:

- Check if headset power is on and headset is linked
- Place headset in ear
- Use mobile phone handset to make call
- Talk directly to microphone once call is connected and answered

To make a new call using voice activated function:

- Press **S1** briefly and wait for headset signal tones
- Say recorded voice command set on your mobile phone (e.g. Call "Name of Person")
- Wait a few seconds for call to connect
- Talk directly to microphone once call is connected and answered

IMPORTANT: Verify mobile phone voice activated function is properly set and headset is within range of the mobile phone

To Redial last number called

- Hold **volume up (+)** button until you hear 4 tones
- Handset will call last number dialed

NOTE: This feature works on mobile phones with the "Handsfree" profiles only

19 20

Ending Calls

To End Call manually:

- Press **S1** briefly to disconnect call
- LED will show blue flashing light every 3 seconds indicating the headset is in stand-by

To end call with auto-end function:

- Call will automatically disconnect
- LED will show blue flashing light every 3 seconds indicating the headset is in stand-by

Call Waiting

NOTE: Call Waiting is a network service, please consult your network provider for details.

To accept an incoming call during a conversation:

- Press **volume up (+)** briefly and the phone will automatically switch to Line 2
- Press **volume up (+)** briefly to switch between lines
- Press **S1** briefly to disconnect the in session call

21 22

Volume

To adjust the headset volume during a call:

- Press and release **volume up (+)** to increase headset speaker volume
- Press and release **volume down (-)** to decrease headset speaker volume
- Headset will give warning tone when maximum or minimum volume is reached

To mute the microphone during an active call:

- Press **volume up (+)** and **volume down (-)** buttons simultaneously for about a second
- Headset microphone will be muted until removed
- Headset will give periodic beep tone indicating mute function is active

To remove microphone mute function:

- Press **volume up (+)** and **volume down (-)** buttons simultaneously
- Microphone mute function is deactivated and microphone is active again

VOICE OVER INTERNET PROTOCOL (VOIP) APPLICATION

The YD-V4 headset can be used with a desktop or laptop computer that are Bluetooth® compatible, to make calls via Voice Over Internet Protocol (VOIP).

To use this function, follow the instructions below:

NOTE: If your computer does not have built-in Bluetooth® capability, you will need to install a Bluetooth® USB adapter to utilize the headset. Follow instructions for installing adapter in your computer.

- Download from the corresponding websites and install Skype, MSN Messenger, Netmeeting, Yahoo messenger, or ICQ application software in the PC
- Pair headset with computer
- Follow pairing instruction for YD-V4 Bluetooth® headset to set the headset into "pairing" mode
- Start the computer Bluetooth® software and pair with the YD-V4 Headset
- If computer prompts for a headset passkey enter **0000**
- Connecting and Disconnecting:
 - o Press the **S1** key briefly to connect the YD-V4 Headset with the computer
 - o Press **S1** briefly again to disconnect
 - o After turning off and turning on the headset, you just need to press **S1** briefly to establish the audio link if the computer was the last used device.

23 24

FCC/ICC

Federal Communication Commission Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules & 682010. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) This device must accept any interference received, including interference that may cause undesired operation.

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

IMPORTANT NOTE:

FCC Radiation Exposure Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

IC Statement:

Operation is subject to the following two conditions:

- 1) This device may not cause interference.
- 2) This device must accept any interference, including interference that may cause undesired operation of the device.

This device has been designed to operate with an antenna having a maximum gain of 0 dB. Antenna having a higher gain is strictly prohibited per regulations of Industry Canada. The required antenna impedance is 50 Ohms.

IMPORTANT NOTE:

IC Radiation Exposure Statement:

This equipment complies with IC radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

25 26

CUSTOMER SERVICE / CONTACT US PAGE

For questions or issues regarding the product, please visit www.letsyada.com or contact Winplus in your area/region to speak to our customer service representative. When contacting customer service please have the manual to your YADA and phone available:

Winplus USA	Tel: 866-294-9244 Tel: 909-752-3074
Winplus Europe	Tel: 44-1440-713888
Winplus Australia	Tel: 61-3-9720-4143
Winplus New Zealand	Tel: 64-9-5254575
Winplus Asia	Tel: 852-2798-8932

You can also contact us online by visiting www.winplus.com for more information about the product.

IF YOU ARE EXPERIENCING ANY ISSUES WITH THE HEADSET DURING OPERATION, DO NOT RETURN THE PRODUCT TO THE STORE. CONTACT WINPLUS DIRECTLY FOR INSTRUCTIONS ON HOW TO RETURN/EXCHANGE THE PRODUCT.

23 24

FCC/ICC

Federal Communication Commission Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules & 682010. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) This device must accept any interference received, including interference that may cause undesired operation.

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

IMPORTANT NOTE:

FCC Radiation Exposure Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

IC Statement:

Operation is subject to the following two conditions:

- 1) This device may not cause interference.
- 2) This device must accept any interference, including interference that may cause undesired operation of the device.

This device has been designed to operate with an antenna having a maximum gain of 0 dB. Antenna having a higher gain is strictly prohibited per regulations of Industry Canada. The required antenna impedance is 50 Ohms.

IMPORTANT NOTE:

IC Radiation Exposure Statement:

This equipment complies with IC radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

25 26