


# 正面



### Table of contents

- 1 Introduction ..... 2
- 2 Kit Contents ..... 3
- 3 Diagram ..... 4
- 4 How to use ..... 5
- 4.1 General function ..... 5
- 4.2 Pairing to mobile phone ..... 6
- 4.3 Charging your Q9 ..... 7
- 5 Technology specification ..... 8
- 6 Notice ..... 8
- 7 Service and Support ..... 9
- 8 FAQ ..... 9

### 1. Introduction






Congratulations, and thank you for choosing the Q9 Bluetooth Headset. This manual will help you operate the Bluetooth Headset, but you should first familiarize yourself with the Bluetooth functionality of your mobile phone before using the Headset Q9.

**Safety Rules**


- 1/ Please follow the rules depicted in this manual closely to ensure your safety. Before using this Headset, we would strongly encourage you to read through this user manual.
- 2/ Be more wary of any edges, uneven surfaces, metal parts, accessories and its packaging so as to prevent any possible injury or damage.
- 3/ Do not modify, repair or dismantle this Headset. Doing so may result in fires, electric shocks, complete breakdown of this Headset, etc. All of which, are not covered under warranty.
- 4/ Do not use any diluents or volatile liquid to clean the Headset.
- 5/ Do not use the Headset in a hazardous location.

### 2. Kit Contents

The package will contain the following

-  1X Bluetooth Headset Q9
-  1X AC Charger
-  1X USB Charger
-  2X Removable Clear Earhooks
-  1X User Manual

### 3. Diagram



### 4. How to use

#### 4.1. General Functions

Desired Result	Required Action
Turn on the hands-free	Press the "action" button for 4 seconds. LED indicator: Blue LED flashes 2 seconds, then off.
Enter the pairing mod	With the headset turned ON, press and hold the "action" button for at least 6 seconds. LED indication: Blue LED quickly flash until paired.
Pairing with a mobile phone	You should use a Bluetooth function mobile phone and to perform pairing action (detail refer to the chapter about pairing). LED indication: Blue LED slowly flash.
Voice Dial	Quick tap the action button twice.
Answer a call	When receive a call, press the "action" button to answer the call.
Reject a call	Press the "action" button at least 4 seconds using the incoming call.
Increase the volume	Tap "+" terminal of the volume button
Decrease the volume	Tap "-" terminal of the volume button
Low battery warning	LED indication: Flashes Warning tone.
Turn off the hands-free	Press the "action" button at least 4 seconds when the hands-free is on.

# 背面

### 4.2. Pairing Q9 to Mobile phone


To use your Bluetooth Headset Q9, you must first pair your Bluetooth Headset to the mobile phone. Pairing is a one time process. Once your Headset is paired to a specific mobile phone, they will remain paired and automatically recognize each other whenever they are within range. If the connection between the phone and Headset is lost, tap the "action" button on the Q9 to reconnect the device.

**Pairing the Headset to a Bluetooth mobile phone:**

- Turn on your phone and ensure its Bluetooth function is activated.
- Turn on the Headset Q9 and continue to press the "action" button about 6 seconds until your headset to enter to pairing mode, then the LED LED flash rapidly.
- Search your Bluetooth devices on your phone by following the phone's instructions. Refer to your phone's user manual for more information.
- After a few second the phone will list the Headset Q9 as a discover device. Select it and follow your phone instruction to select this pairing.
- Then your phone will request a passkey or PIN, enter 0000 as your PIN or passkey.
- Your phone will confirm the pairing, and then press Yes/OK. After it, the LED of your Q9 will turn off the flash.
- Finally, select to connect with your Q9 from your phone.

### 4.3. Charging your Q9

The Headset Q9 is convenient to connect to AC charger or a USB charger with Mini DC 2.0 port. Make sure that your Bluetooth Headset Q9 is fully charged for at least 4 hours before initial use. Insert one terminal of your charger to AC main or USB port of PC and other terminal to DC 2.0 jack on side of Q9. While charging, the LED of Q9 light constantly. When charging is completed, the LED turns off.



**Warning:**

- You must select a qualified charger from a regular manufacturer.
- You must charge the Headset if it has been not used for more than 12 months.

### 5. Technical specification

- Talk time: up to 6 hours.
- Standby time: up to 120 hours.
- Weight: 6.5 g.
- Dimensions (33x14MM):
- Range up to 10m.
- Bluetooth V2.0+EDR
- Supported profiles: Handsfree v1.5 & Headset v1.1

### 6. Notice

**FCC Information FCC ID: V09-QNINE**  
This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:  
(1) This device may not cause harmful interference, and  
(2) this device must accept any interference received, including interference that may cause undesired operation.

**European CE Notice**  
The Bluetooth Headset is in compliance with the following essential requirement of Council Directive 1999/5/EC (refer to the R&TTE Directive): Articles 3.1a, 3.1b and 3.2. The product is manufactured in accordance with the Annex 2 of the above directive.

**Declaration of conformity (DOC)**  
The Bluetooth Headset is compliant with and successfully passed all the interoperability tests that are specified in the Bluetooth specification. However, interoperability between the device and other Bluetooth enable products is not guaranteed.

### 7. Service and Support

If your Bluetooth Headset is not performing as it should, please take it to your local service providers or dealer for service.

For additional information please visit our website at: [www.Quikcell.com](http://www.Quikcell.com)

### 8. FAQ

- 1) Why is there no power even when the Headset is power on?  
**Ans:** Ensure the battery is being charged up to 4 hours for first time using. The LED is lighted when it starts charging.
- 2) There is no sound when answer a call.

**Ans:** Check to see if the volume is adjusted too low. If it is too low, turn it up. Make sure the Headset is paired and connected with your target phone.

3) How can I know the Headset has been fully charged?  
**Ans:** When the indicator LED turns off from on when it is charging, it has been fully charged.

**Limited Warranty**

- 1) If within 12 months of purchase this device or any part thereof is proven to be defective by reason of faulty workmanship or defects in materials, we will at our option repair or replace the same free of charge of labor or materials on condition that:
- 2) The original invoice or sales receipt with the date or purchase, or stamp from the dealer is presented together with the defective unit.
- 3) The warranty does not cover Product failures which have been caused by use of accessories or other peripheral devices which are not original accessories intended for use with the Product.
- 4) The warranty does not cover Product failures caused by:
  - Modification, repaired, and assembled by any person who is not authorized by the manufacturer.
  - Any defective unit or part shall become property of the manufacturer.
  - 5) The warranty does not cover any damage caused by misuse, drop, hit or neglect.

**FCC STATEMENT**

1. This device complies with Part 15 of the FCC Rules.
2. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

**RF warning statement:**

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.