# FCC ID: WAD-BTH026A Bluetooth stereo headset User's manual



# **Contents**

■ Brief introduction	1
■ Before use	1
1. Overview	1
2. Charging for headset	2
■ Getting started	3
1. Turning on/off the headset	3
2. Wearing the headset	3
3. Pairing/connecting.	4
1) Pairing headset with Bluetooth cell phone via Bluetooth	4
2)Pairing headset with Bluetooth transmitter via Bluetooth	15
3) Pairing headset with multi devices via Bluetooth	6
4.Battery display	6
5. Making a call with the headset	7
6. Playing music	9
7. LED indicator	10
8. Factory Reset	10
■ Care and maintenance	10
■ FAOs	11


Welcome to use this Bluetooth stereo headset, BTH026A. Please read this user's manual carefully before use.

## **■** Brief introduction

BTH026A is a sports Bluetooth stereo headset, with IPX4-rated sweatproof on the remote control.Mini and portable design for easy taking. You can use it to enjoy wireless music and make a call at the same time.

### ■ Before use

### 1. Overview





1	Cover of charging jack	6	LED indicator
2	Micro USB charging jack	7	Microphone
3	▲ :volume up/previous song	8	Big/middle/small eartips
4	<b>b</b> : Multi-functions button	9	Stabilizer
5	▼: volume down/next song		

2. Charging for headset

The headset comes with a built-in rechargeable battery, prior to using it, it is recommended to charge the battery fully for the first time.

When the headset is low power, the headset emits "Battery Low" every 1 minutes and LED flashes like "red LED-blue LED". Please recharge the battery of the headset.

The way of charging as following:


## Using USB cable

- 1. Turn on the cover of charging jack, and plug the USB charging cable
- 2. Plug another side of cable to the USB port of PC

Red light on: Charging

Red light off: Finish charging

3. It will takes about 2 hours to finish charging



### Remarks:


- The battery is recyclable.
- Batteries (battery pack or batteries installed) shall not be exposed to excessive heat place, such as sunshine, fire or the like.

## ■ Getting started

1. Turning on/off the headset


Functions	Operation	Prompt tone
Turning on	Press and hold <b>0</b> about 3	Power on
	seconds until blue LED flashes	
Turning off	Press and hold <b>0</b> about 3	Power off
_	seconds until red LED flashes	

**Remark:** In order to save power, the headset will turn off automatically if no devices can be connected after 5 minutes.



## 2. Wearing the headset

a. Put the stabilizer into the headset and rotate to the suitable position as following shown:



b. Choose the suitable size eartips according to your ear and wear to the headset.

c. Wear the headset to your ear in L/R direction, and rotate the headset to get best comfortable feeling.





c. Set up the cord management clips to get better wearing as following shown:





3. Pairing/connecting

1) Pairing headset with Bluetooth cell phone via Bluetooth

Prior to using the headset for the first time, you have to pair it with a Bluetooth-enabled cell phone. The pairing procedures are subject to different models of cell phones. Please refer to your cell phone user's manual for further information.

The general pairing procedures are as follows:

- 1) Keep your headset turned off and within 1 meter of phone;
- Press and hold b about 6 seconds until the red and blue LED flash alternately, the headset enter into paring mode and emits "Pairing";
- Activate your cell phone's Bluetooth function and search for Bluetooth devices within range, select "BTH026A" from the list of devices shown (enter password "0000" if the headset prompt);
- 4) After successful connecting, blue LED of headset flashes twice every 4 seconds and emits "Connected".

### Remarks:

- Pairing mode will last 2 minutes, the headset will back to standby mode if the pairing failure.
- Every time the headset is turned on, it will connect to last connected device automatically.
- When the headset is on without connecting any other devices, short press
   it will connect to the last pairing devices.
- When the headset and devices are out of range it will disconnected, and reconnecting automatically if return back effective range within 5 minutes. To save power the headset will turn off automatically after 5 minutes.
- 2)Pairing headset with Bluetooth transmitter via Bluetooth.

You can connect the headset to a Bluetooth transmitter to enjoy music wireless. Hereby take BTT005 (Bluetooth transmitter, not included in accessories) for example. The pairing steps are as follows:

- 1) Keep your headset and transmitter within
- 1 meter when pairing;
- 2) Make the headset enter pairing mode
- (Please refer to "How to enter pairing mode):
- 3) Turn on the Bluetooth transmitter and make it enter paring mode. It will search for

Bluetooth devices automatically and send a pairing request;

4) After successful pairing and connecting,

blue LED of the headset flashes twice every 4 seconds .

### Remarks:

- a) The pairing password of BTH026A is "0000". So, the headset can only pair with a Bluetooth transmitter whose pairing password is "0000".
- b) If pairing still fails after several tries, please refer to the Bluetooth transmitter's user's manual for further information.

## 3) Pairing headset with multi devices via Bluetooth

The headset can connect with two Bluetooth cell phones at the same time. The general pairing procedures are as follows:

- 5) Pairing the headset with device one
- Turn on the headset and make it enter pairing mode again, and pairing it with device two
- Operate device one to connect with headset. The headset has already connected with two devices in this moment. Or restart BTH026A it will connecting two devices automatically.

## 4. Battery display

When the headset connected with IOS device, it will display the battery of the headset on the device. When the headset is in low battery, power symbol show red, it emits you to charge for your headset.







**Battery Low** 

# 5. Making a call with the headset 1) Basic operation

Functions	Status of	Operation	Prompt tone
	headset		
Cancel a call	Calling	Short press <b>b</b>	Call
		once	terminated
Answer a call	Incoming call	Short press <b>b</b>	Answer
	ringing	once	
Reject a call	Incoming call	Long press <b>b</b>	Reject
	ringing	about 2 seconds	
End a call	During a call	Short press <b>b</b>	Call
		once	terminated
Volume up	During a call	Short press ▲	
		button	
Volume down	During a call	Short press ▼ button	
Transfer conversation	During a call	Long press <b>O</b> about 2 seconds	Transfer audio
to mobile		about 2 seconds	audio
phone			
Transfer	During a call	Long press <b>b</b>	Transfer
conversation		about 2 seconds	audio
to headset			
Microphone	During a call	Long press "▲"	Mute on
mute		about 2 seconds	
Cancel mute	During a call	Long press "▲"	Mute off
	(microphone	about 2 seconds	
	mute)		
Voice dial	Standby mode	Short press <b>b</b>	Voice dia
	(connected	and"▲"	
	device)	button	
		simultaneously	

Redial the last number	Standby mode (connected	0.00	Last number redia
	device)		

Warning: Excessive pressure from earphones and headphones can cause hearing loss.

### Note:

- To get the best calling effect make your microphone closer to your mouth.
- When the volume is adjusted to max, it emits "Maximum volume"; and emits "DU" when adjusted to min.
- When the headset under microphone mute mode, you will hear "Mute on" continuously every 10 seconds.
- When pressing the answer button on some mobile phones, the call will be transferred to the mobile phone. You can switch the call to the headset by using the conversation switch button or through operating on the mobile phone. Please refer to your mobile phone user manual for further information.

## 2) Three-ways call operation

Functions	Status of headsets	Operation	
Answer new call and	There are second Short press <b>b</b> once		
end current call	incoming call		
Answer new call and	There are second	Double click <b>b</b>	
retain current call	incoming call	button	
Switch calls	Keep conversation	Double click <b>b</b>	
		button	
End current call and	Keep conversation	Short press <b>b</b> once	
switch retain call			

3) Connect with two cell phones

5) Connect with two cen phones			
Functions	Status of headset	Operation	
End phone call #1 and answer phone call #2	During phone call #1, phone 2 has incoming call	Short press <b>O</b> once	
Retain phone call #1 and answer phone call #2	During phone call #1, phone 2 has incoming call	Double click <b>b</b>	
Switch call	During call, one of phone call is retained	Double click <b>O</b> button	
End current call, back to retain phone call	During call, one of phone call is retained	Short press <b>O</b> once	

6. Playing music

Functions	Status of the headset	Operation
Volume up	Playing music	Short press "▲"button
Volume down	Playing music	Short press "▼"button
Last song	Playing music	Long press "▲"button
Next song	Playing music	Long press "▼"button
Pause	Playing music	Short press O once
play	Pausing	Short press O once

### Notes:

- When the volume is adjusted to max, it emits "Maximum volume"; and emits "DU" when adjusted to min.
- If you want to remote control last/next song, pause/play, it needs your Bluetooth mobile phone or Bluetooth transmitter paired with the headset to support AVRCP profile, please refer to the user's manual of your mobile phone or Bluetooth transmitter for further information.

### 6. LED indicator

LED indicator	Status of headset
Red and blue LED flashes	Pairing mode
alternately	
Blue LED flashes once every 4	Not connected to device
seconds	
Blue LED flashes twice every 4	Connected to device
seconds	
Red LED flashes before blue	Low battery
LED	· -

### 8. Factory Reset

In the status of power off, long press "\underwar" + "\underwar" button about 6 seconds and release it until the red and blue LED flashes simultaneously, you will hear prompt tone "DUDU".

### Remarks:

After factory reset, the paired list of headset will be deleted. After turn it on again, the headset will enter pairing mode automatically, and you need to re-pair and connect with Bluetooth devices.

### ■ Care and maintenance

Read the following recommendations carefully before using BTH026A. Following these you will be able to enjoy this product for many years.

- Keep it dry and don't put it in the dump place to avoid the product's internal circuit being affected.
- Keep the product away from direct sunlight or hot places. High temperatures will shorten the life of electronic devices, destroy the battery or distort certain plastic parts.
- Don't expose the product to cold areas. It may damage the internal circuit board.
- Don't try to disassemble the product as it may get damaged if you are not professional.
- Don't let it fall down onto the floor or other hard surfaces. The internal circuit might get damaged.
- Don't use intensive chemical products or detergent to clean the product.
- Don't scratch the surface with sharp things.
- Don't use this product during strenuous exercise. It may get damaged by sweat.

In case the product doesn't function properly, send it to the store you bought it. The staff will help you to solve the problem

## ■ FAQs

1. What does it mean when red LED flashes before blue LED?

Battery is low power, need to be recharged.

## 2. Why is the red LED off when charging?

- a) Please make sure the charging device connect with headset Well;
- b) The battery may dry up. Please charge the battery for 30 minutes, and then the red LED will be ON.

## 3. Why can't I hear the sound on the headset?

- c) Make sure the headset has been switched on;
- d) Make sure the volume is not too low or muted;
- e) Make sure the headset connects with the mobile phone correctly;
- f) Make sure the distance between the headset and the cell phone is in the available Bluetooth range.

## 4. Why can't I hear the sound clearly on the headset?

- a) Make sure the mobile phone is in the strong signal area;
- b) Make sure the headset is in the available range of this product.
- 5. Why the pause/play, last/next song not function when playing music? Make sure your Bluetooth device supports AVRCP (Audio/Video Remote Control profile)

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- -Consult the dealer or an experienced radio/TV technician for help

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.