BTH033 Bluetooth stereo headset User's manual



Contents

■ Brief introduction	
1. Bluetooth wireless communication technology	1
2. About BTH033	
■ Before use	
1. Overview	
2. Charging for Headsets	
■ Getting started	
1. Turning on/off the headsets	4
2. Pairing headsets with Bluetooth devices	4
1) How to enter pairing mode	4
2) Pairing headsets with Bluetooth devices	5
3) Pairing headsets with Bluetooth transmitter	
4) Pairing headsets with Multi-devices	
3. Reconnecting the headsets with devices	
4. Making calls with the headset	7
5. Playing music	9
6. LED indicator	10
7. Indication tone	10
8. Factory Reset	11
9. Resetting	
■ Care and maintenance	
FAQs.	
■ Specification	12

Welcome to use this Bluetooth stereo headset, BTH033. Please read this user's manual carefully before use.

■ Brief introduction

1. Bluetooth wireless communication technology

Bluetooth is a standard of close range wireless communication technology that was drawn up by Ericsson, IBM, Intel, Nokia and Toshiba, With Bluetooth technology, we can achieve the highest transmission rate among cell phones, computers, printers, PDAs and other devices. The max transmission range of class II is 10 meters while the max transmission ranges of class I can reach up to 100 meters.

2. About BTH033

BTH033 is a Bluetooth stereo headset. Foldable and retractable design is very easy to take with you. It supports the following Bluetooth profiles:

HSP — Headset Profile

HFP --- Hands-free Profile

A2DP —— Advanced Audio Distribution Profile

AVRCP Audio/Video Remote Control Profile

You can enjoy music wirelessly by using BTH033. It has the following features:

- 1) Pairing with a Bluetooth cell phone or PDA supporting HFP profile.
- Answer a call, end a call and reject a call
- · Redial last number
- Voice dial
- Adjust the volume
- Call transfer between the headset and your Bluetooth cell phone
- Microphone mute
- 2) Pairing with a Bluetooth music device or Bluetooth transmitter supporting A2DP profile.
- ◆ Enjoy music wirelessly Adjust the volume
- ◆ Remote control pause/play
- ◆ Remote control previous/next track

- 3) Easy to switch between the call and music, you will not miss the incoming call during listening to music.
- 4) Every time the headset is turned on, it will connect to last connected device automatically.

Note: In order to complete to above function, the Bluetooth profiles of paired device must be same as the headset. And even though the paired device and the headset support the same Bluetooth profiles, functions may vary due to specification differences of the paired devices.

■ Before use

1. Overview





1	Built-in Microphone	7	LED indicator
2	Multi-function button(MFB)	8	Charging jack
3	Next song	9	Volume down
4	Pause/play	10	Volume up
5	Last song	11	Right speaker
6	Line-in jack	12	Left speaker

2. Charging the headset

The headset comes with a built-in rechargeable battery, prior to using it, it is recommended to charge the battery fully for the first time.

When the headset is low power, red LED flashes twice and the headset emits three "Dong" tones every 30 seconds and the red LED flashes twice. Please recharge the battery of the headset.

The way of charging as following:

Using USB cable

- 1. Plug USB charging cable into the USB port of computer
- 2. Plug another side of USB cable to headset

Red light on: Charging

Red light off: Finish charging

3. It will takes about 2.5 hours to finfish charging



Remarks:

- 1) The battery is recyclable.
- Batteries (battery pack or batteries installed) shall not be exposed to excessive heat place, such as sunshine, fire or the like.

■ Getting started

1. Turning on/off the headset

Functions	Operation	LED indicator
Turning on	Press and hold MFB button for	Blue LED on one
	3~5 seconds until blue LED	second
	flashes	
Turning off	Press and hold MFB button for	Red LED on one
	3 seconds until red LED	second
	flashes	

Remark: In order to save power, the headset will turn off automatically if no devices can be connected after 5 minutes

2. Pairing the headset with Bluetooth devices

1) How to enter pairing mode

Functions	Operation	LED indicator
Entering	Ensure the headset is off, and	Red and blue LED
pairing	then press and hold MFB	flash alternately
mode	button for 7~8 seconds until red	
	and blue LED flash alternately	

Remark: Pairing mode will last 2 minutes. If no devices can be connected after 2 minutes, it will return to standby mode automatically.

2) Pairing the headset with a Bluetooth cell phone

Prior to using the headset for the first time, you have to pair it with a Bluetooth-enabled cell phone. The pairing procedures are subject to different models of cell phones. Please refer to your cell phone user's manual for further information. The general pairing procedures are as follows:

- 1) Keep your headset and phone within 1 meter when pairing;
- Make the headset enter pairing mode (please refer to "How to enter pairing mode);
- Activate your cell phone's Bluetooth function and set your cell phone to search for Bluetooth devices within range, and select "BTH033" from the list of devices shown;
- 4) According to the indication, enter password or PIN No: "0000";
- 5) If prompted by your cell phone to connect, select "Yes" (this will vary among cell phone models);
- 6) After successful connecting, blue LED flashes twice every 4 seconds or flashes three times every 4 seconds.

Remarks:

- ◆ If pairing is failed, please turn off the headset first and then re-pair according to steps 1 ~ 6 mentioned above.
- After pairing is successful, the headset and the cell phone will remember each other, they will no need to re-pair next time. The headset can remember 8 paired devices, when the number of paired devices exceeds 8, the first one will be replaced.
- Every time the headset is turned on, it will connect to last connected device automatically. If you want to pair it with other devices, please turn off the Bluetooth function of last connected devices first and pair the headset with the new device according to steps 1 ~ 6 mentioned above.

3) Pairing the headset with a Bluetooth transmitter

You can connect the headset to a Bluetooth transmitter to enjoy music wirelessly. Hereby take BTT010 (Bluetooth transmitter for iPod and iPhone, not included) for example. The pairing steps are as follows:

- 1) Keep your headset and phone within 1 meter when pairing;
- Make the headset enter pairing mode (Please refer to "How to enter pairing mode);
- Turn on the Bluetooth transmitter. It will search for Bluetooth devices automatically and send a pairing request;
- 4) When the headset requests to enter a PIN No., the transmitter will response "0000" automatically:
- 5) After successful pairing and connecting, blue LED of the headset flashes twice every 4 seconds.



Remarks:

- The pairing password of the headset is "0000". So, the headset can only pair with a Bluetooth transmitter whose pairing password is "0000".
- ◆ If pairing still fails after several tries, please refer to the Bluetooth transmitter's user's manual for further information.

4) Multi-pairing

The headset can connect with two devices at most. One is a Bluetooth cell phone supporting HFP profile, the other one is a Bluetooth music device supporting A2DP profile. If you want to finish the multi-pairing, please refer to the following steps:

- 1) Firstly, pair the headset with a Bluetooth transmitter (refer to "pairing the headset with a Bluetooth transmitter);
- 2) Turn off the Bluetooth transmitter;
- 3) Pair and connect the headset with a Bluetooth cell phone (refer to "pairing the headset with a Bluetooth cell phone");
- **4)** Turn on the Bluetooth transmitter, it will connect to the headset automatically.

Remarks:

- After successful multi-pairing, the paired devices will remember each other, they will no need to pair next time. If the pairing information is deleted, please connect the mobile phone with the headset first and then turn on the Bluetooth transmitter, multi-connecting can be performed.
- For the cell phone supporting the HSP and A2DP at the same time. It
 may set up HSP and A2DP connection with the headset simultaneously.
 At this time, the Bluetooth transmitter may not connect to the headset.

3. Re-connecting with a Bluetooth device

1) Automatic connecting

Every time the headset is turned on, it will connect to last connected device automatically.

2) Manual connecting

When the headset is in standby mode and doesn't connect to a device, short press MFB button once, it will connect to last connected device.

Remarks:

- Before connecting to a Bluetooth device, please turn on the Bluetooth function of Bluetooth device.
- On some Bluetooth devices, take some Nokia cell phones for example, you have to allow automatic connecting in the cell phone's settings. Please refer to your cell phone's manual for further information.

4. Making a call with the headset

1) Basic operation

Functions	Status of headset	Operation
Cancel a call	Calling	Short press MFB once
Answer a call	Incoming ringing	Short press MFB once
Reject a call	Incoming ringing	Long press MFB for 2 seconds and release it until listen a tone
End a call	During a call	Short press MFB once
Volume up	During a call	Short press+ button
Volume down	During a call	Short press — button

Transfer conversation to mobile phone	During a call	Long press MFB for 2 seconds
Transfer conversation to headset	During a call	Long press MFB for 2 seconds
Microphone mute	During a call	Double click MFB
Cancel mute	During a call (microphone mute)	Double click MFB
Voice dial	Standby mode (connected device)	Long press ► button for 2 seconds
Redial the last number	Standby mode (connected device)	Double click MFB
Remove paired list	Turned off	Press MFB and pause button for 8 seconds simultaneously, and release it until the red and blue(or purple) LED on at the same time

2) Three-ways call operation

Functions	Status of headsets	Operation
Answer new call and	There are second	Short press MFB
end current call	incoming call	once
Answer new call and	There are second	Long press MFB for
retain current call	incoming call	2 seconds
Switch calls	Keep conversation	Long press MFB for
		2 seconds
End current call and	Keep conversation	Short press MFB
switch retain call		once

Warning: Excessive pressure form earphones and headphones can cause hearing loss.

Note:

- ◆ Not all the mobile phones support all the functions listed above. Please refer to your mobile phone user's manual.
- Different function and prompt tone according to different mobile phone.
- When the volume is adjusted to max or min, you will hear one prompt tone.
- When pressing the answer button on some mobile phones, the call will be transferred to the mobile phone. You can switch the call to the headset by using the conversation switch button or through operating on the mobile phone. Please refer to your mobile phone user manual for further information

5. Playing music

When the headset connects to a mobile phone or Bluetooth transmitter which supports A2DP, you can enjoy music wirelessly through the headset.

Function	Status of the	Operation
	headset	
Volume up	Playing music	Short press "+"button
Volume	Playing music	Short press "-"button
down		
Last song	Playing music	Short press ◀ button once
Next song	Playing music	Short press ▶ button once
Pause	Playing music	Short press ▶∥ button once
play	Pausing	Short press ▶∥ button once
Line in	Turned off	It can playing music through 3.5mm
input		audio line

Notes:

- When playing music on some mobile phones, the music will be transmitted to the mobile phone's speaker instead of the headset. You have to select "transmit the sound via Bluetooth" in the settings menu and then choose "BTH033" as speaker device. The music will be transmitted to the headset. Please refer to your mobile phone's user's manual for further information.
- When the volume is adjusted to max or min., you will hear one prompt tone.

- If you want to remote control last/next song, pause/play, it needs your Bluetooth mobile phone or Bluetooth transmitter paired with the headset to support AVRCP profile, please refer to the user's manual of your mobile phone or Bluetooth transmitter for further information.
- The Bluetooth will disconnect between headset and mobile phone automatically if you plug 3.5mm audio input, and the Line in is available in this time

6. LED indicator

1) Charging

LED indicator	Status of headset
Red LED on	Charging
Red LED off	Finish charging

2) Pairing with Bluetooth device

LED indicator	Status of headset
Red and blue LED flashes	Pairing mode
alternately	
Blue LED flashes once quickly	Not connect device
every 2 seconds	
Blue LED flashes twice quickly	Have already connected HFP or
every 4 seconds	A2DP
Blue LED flashes three times	Connect HFP and A2DP
quickly every 4 seconds	simultaneously
Blue LED flashes quickly	Calling/incoming call
Blue LED flashes once quickly	During a call
every 4 seconds	-
Red LED flashes twice every 30	Low battery
seconds	

7. Indication tone

Indication tone	Status of the headset
Continuous two prompt tone	Conversation mode and
every 10 seconds	microphone mute
Three "dong" warning tone every	Low battery
30 seconds	-

8. Factory Reset

In the status of turned off, long press MFB and pause button for 8 seconds simultaneously and release it until the red and blue LED on.

9. Resetting

If the product work abnormally, you can plug 3.5mm Line-in or charging the headset so that to reset products.

■ Care and maintenance

Read the following recommendations carefully before using BTH033. Following these you will be able to enjoy this product for many years.

- Keep it dry and don't put it in the dump place to avoid the product's internal circuit being affected.
- Keep the product away from direct sunlight or hot places. High temperatures will shorten the life of electronic devices, destroy the battery or distort certain plastic parts.
- Don't expose the product to cold areas. It may damage the internal circuit board.
- Don't try to disassemble the product as it may get damaged if you are not professional.
- Don't let it fall down onto the floor or other hard surfaces. The internal circuit might get damaged.
- Don't use intensive chemical products or detergent to clean the product.
- Don't scratch the surface with sharp things.

In case the product doesn't function properly, send it to the store you bought it. The staff will help you to solve the problem

■ FAOs

 What does it mean when red LED blinks twice every 30 seconds? Battery is low power, need to be recharged.

2. Why is the red LED off when charging?

- a) Please make sure the charging device connect with headset Well;
- b) You didn't use the headset for a long time, the battery may dry up. At this time, you have to charge the battery for 30 minutes, and then the red LED will be ON.

3. How far is the effective rang between the headset and mobile phone?

According to the Bluetooth standard, the max available range of ClassII headset is 10 meters. It varies under different environment.

4. Why my mobile phone can not search and find the headset?

The mobile phone will not find the headset if headset and mobile phone are not under the pairing mode. Make sure the headset is under the pairing mode and in the effective working range, and then the headset can be paired and connected.

5. Why can not hear the voice?

- a) Make sure the headset has been switched on:
- b) Make sure the volume is not too low or muted;
- c) Make sure the headset connects with the mobile phone correctly;
- d) Make sure the distance between the headset and the cell phone is in the available Bluetooth range.

6. Why is the voice not clear in conversation?

- a) Make sure the mobile phone is in the strong signal area;
- b) Make sure the headset is in the available range of this product.

7. Why can't control pause, play, last song and next song when playing music?

This function needs your Bluetooth device supports AVRCP (Audio/Video Remote Control profile)

■ Specifications

Bluetooth version	Bluetooth V2.1+EDR
Bluetooth profiles	Headset, Hands free, A2DP, AVRCP
Operating distance	10meters
Headset working time	Music up to 17 hours
Headset standby time	Approx 384 hours
Charging input	DC5.0V === 340mA
Headset charging time	Approx 2.5 hours
Dimension	176*165*32mm
Weight	Approx 172.8g
Battery capacity	415mAH

Warning: This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- > Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- ightharpoonup Consult the dealer or an experienced radio/TV technician for help.