

Bluetooth Headset user Guide



ITEM#BH-M10B

General Functions:

Turning On:

Press and hold the multi-function button for 5 seconds, indicator light will flash blue 3 times.

NOTE: For the first 5 cycles of turning on the headset, the headset will beep twice, and then flash blue 5 times, and then two times.

Turning Off:

Press and hold the multi-function button for 5 seconds, the headset will beep 3 times, and the indicator light will flash red 3 times.

Voice Dialing:

Press the multi-function button.

Redialing:

Press the multi-function button twice.

Answering/Ending a Call:

Press the multi-function button once.

Mute On/Off:

Press and hold Volume (-) for 2-3 seconds.

*Some functions may or may not work with certain phone models. See your phone's manual for more information.

-3-

Charging The Headset:

This headset includes a built-in Lithium Polymer battery. To charge the unit:

1. Plug the charger into proper outlet.
2. Plug the unit end of charger into the power outlet of headset.
3. During charging, the indicator light will turn red. When charging is complete, the indicator light will shut off or flash red to alert you that the headset is fully charged.

NOTE:

- * For first time use, make sure to fully charge the headset at least for 4 hours, or preferably overnight (8-10 hours).
- * If headset has not been used for more than 21 days, recharge unit for at least 4 hours or preferably overnight (8-10 hours).
- * Do not use the headset during charging.
- * Please only use original charger included in the packaging.
- * If indicator light flashes red during usage or while on standby, the battery is low, and you should recharge the unit as soon as possible.
- * Recharge unit only in places at room temperature.

Wearing The Headset:

This headset can be worn according to your preference, just adjust the microphone.

-4-

Specifications:

Model Number: BH-M10B

Signal Output: Bluetooth v2.1, Class 2

Talk Time: Up to 18 hours

Standby Time: Up to 180 hours

Profiles: Headset & Handsfree

Connections: Up to 2 devices simultaneously

Data Encryption: 128 bits encrypted

Safety Regulation: CE, FCC, BQB

Overview:

Thank you for purchasing this headset. Please double check the contents of the packaging to verify that you have received all items. Be sure the completely read the user guide before using the headset. This headset can be connected/paired with any device that is Bluetooth wireless technology enabled.

Getting Started:

Please fully charge headset after removing it from the package before beginning the pairing process.

-1-

Pairing the Headset:

Pairing is the professional word for the process of connecting a Bluetooth wireless technology product to a Bluetooth wireless technology enabled device. This process only needs to be completed one time with each new device.

Pairing to 1 device:

1. Press and hold the multi-function button for about 8 seconds, until the indicator light alternates between blue and red, indicating that it is in pairing mode.
2. Activate the Bluetooth search feature on your phone, refer to your phone's manual for further instructions.
3. Select BT PRO from the searched device listing.
4. Enter pin code "0000" to confirm and finish pairing. The headset will flash just blue to indicate completed pairing.

Pairing to 2 devices:

This headset contains a dual-link function for connecting with 2 mobile phones simultaneously.

1. Pair the first phone following the steps above.
2. Temporarily turn off the first connected phone's Bluetooth wireless technology function.
3. Pair the second phone using the steps above.
4. Turn off the headset, and re-turn on the first phones Bluetooth wireless technology functionality.
5. Re-turn on the headset, and it will re-connect to both devices automatically.

-2-

Troubleshooting:

- * Ensure that the headset has enough power, is turned on, and has successfully been fully paired with the mobile device.
- * Ensure that the Bluetooth function on the phone is enabled.
- * Be sure that the range between the headset and mobile device is less than 32 feet (10 meters), or that there is no disturbances or electrical devices between the headset and mobile device.
- * Headset indicator light is flashing red: Low battery
- * During charging indicator light does not illuminate: Leave on charger for 20 more minutes and re-check.
- * No sound coming from headset: 1. Make sure headset is turned on, 2. Make sure headset was fully paired, 3. Make sure distance between headset and device is less than 32 feet.

Headset Storage:

- * Only use original included accessories with this device.
- * Do not disassemble headset. It will void the warranty.
- * Store headset away from dust, heat, and water.
- * Use clean, soft, static-free cloth to clean headset surfaces.
- * Do not allow children to play or use headset.
- * Do not store headset or chargers in extreme environments.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and

-5-

(2) this device must accept any interference received, including interference that may cause undesired operation.

statement:

(1)changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
(2)This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

-6-