

DACOM 大康
MAKE A MELODY WORLD

Sporty Stereo Bluetooth Headset
FCC ID:WTDG10

Knight

Specification

Item : Knight	Bluetooth Version : Bluetooth 4.1
Music Player : Support	DNR(Digital Noise Reduction) : Support
Talk/Playing Time : Up to 7 hours	Standby Time : About 150 hours
Battery : Rechargeable Lithium Polymer Battery	Operation Range : Up to 10 m
Music Control Function : Previous track, Next track, and skip the track.	
Power Display : iOS System Power Display	
Compatibility of Bluetooth Device : Compatible with all Bluetooth Mobile Phone	
Built-in Functions : Voice Prompt, Incoming Number Report, Incoming Number Answer or Reject, Last Number Redial, Auto Call Back.	
Support Connecting Two Bluetooth Devices at the Same Time (Only Can Output One Device Sound at One Time)	



Pairing Steps



Answering/Ending/Redialing



Answering a call

Short press the "MFB"



Ending a call

Short press the "MFB" during a call



Rejecting a call

Long press the "Volume Down" button for about 1 Second



Redialing the last called number

Double press the "MFB" when the headset is in standby mode

Power On / Power Off

Power On- press and hold the "MFB" for about 1 second until the blue light flashes.

Power off- With the status of power on, press and hold the "MFB" for about 3 second until the indicator light goes off.

Charging the headset

Your headset uses a rechargeable battery, you must charge the battery fully before using the headset for the first time.

Plugging the charging cable in the USB Charging socket. The red indicator light remains solid when charging. The fully charging takes about 3 hours. The red indicator light goes out and the blue indicator light remains solid when charging completed.

Answering/Ending/Redialing a call

Answering a call- Press the answer key on your phone or Short press the "MFB" .
Ending a call-Press the end key on your phone Or Short press the "MFB" .
Rejecting a call- Press the end key on your phone Or Long press the "Volume Down" button for about 1 Second.

Redialing the last called number/ Voice dialing

Redialing the last called number- Double press the "MFB" when headset is in standby mode.
Voice dialing- Your phone must support this function, with the headset in standby mode, single press the "MFB" for 1 second

Playing music

Playing Music- When you are listening to the music, you can short press the "MFB" to play and pause.
Previous/Next- For Next Track, press the "Volume down" button for about 1 second. For Previous Track, press the "Volume up" button for about 1 second.
Volume control- To increase the volume, short press the "Volume Up" button. To decrease the volume, short press the "Volume Down" button.

Call transferring /Muting/ Power Alarm

Call transferring- To transfer a call , press the "Volume UP" button for 1 second, short press the "MFB" back to the call.
Muting- For muting, press the "Volume Down" button for 1 second , re-press the "Volume Down" button for 1 second to recovery.
Power Alarm- There will be a power alarm when the headset voltage is lower than 3.3V. The headset will be power off automatically when the headset voltage is as lower as 3V.

Pairing your Bluetooth Device

The distance between the Bluetooth headset and your phone would be better within 1 meter when pairing.
With the headset power off, press the "MFB" button for 3 seconds, the red light and blue light flash alternately, hence, the headset is in pair mode.
Set the phone to search for Bluetooth device.
When the list of detected devices, select "Knight" and confirm.
Enter pin code "0000" when prompted by phone.
When pairing successfully, the blue light will flash.

Pairing Two Devices at Once

1. After paired the first mobile phone, please turn off the Bluetooth function of the first mobile phone, then pair to the second mobile phone
2. Turn on the Bluetooth function of the first mobile phone, manual connection the first mobile phone.
3. During a call, short press the "MFB" to hung up the current call and answer an incoming call ; Double press the "MFB" to answer another incoming call and switch between the two incoming calls.
4. Short press the "MFB" to cut off the incoming calls one by one.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.