



BluStream FM
User Manual



BT43IS Rev C

ABOUT THIS PRODUCT

FM Transmitter for Hands-Free Calling and Streaming Audio through your Car's Speakers

Features

- Works with any FM radio
- Compatible with a wide variety of smartphones and tablets
- Built-in microphone so you can conveniently receive and make calls hands-free while still enjoying your music
- Easy to connect, easy to use

Did You Know: BluStream FM can pair up to 5 devices in its memory, and connect to 2 devices simultaneously!

BOX CONTENTS

Be careful when removing all items from the packaging tray.
Take care not to tug or pull on cables.



BluStream FM transmitter (A)
Plug into your car's 12v socket (cig port)



BluStream module with control button and built-in mic (B)
Mounts onto your vehicle's dash





INSTALLATION SETUP

iSimple knows that your car dash might look different than this illustration. Placement of product will vary per year/make/model of your vehicle.

INSTALLATION INSTRUCTIONS



Step 1

BluStream FM needs a little power to rock your world, so plug the FM transmitter (A) into your 12V power outlet (cigarette port).



Step 2

Mount your BluStream FM module (B) with the included adhesive tape to clean, smooth surface.

NOTE: Make sure you are parked in a safe spot before installation or whenever you are pairing a device. NEVER WHILE DRIVING.

TUNING/SETTING THE RADIO STATION (UP TO 3 PRESETS CAN BE STORED)



Step 1

Tune your car's FM radio to a unused frequency that does not have a station broadcasting... just static.




Step 2

Using the left and right buttons on the FM Transmitter (A), set the frequency to match the selected frequency on your radio.

Note: if you pause on a station for longer than 5 seconds, it will be stored as a preset.

PAIRING GUIDE

Make sure the Control Button LED is flashing blue/red. (If it's not flashing, the unit turned off/timed out. The user will need to press the Control Button to turn on.) The unit shuts off automatically in 5 minutes.



Pairing BT43IS Rev C to Your Phone

Open the Bluetooth menu on your smartphone, and scan for available Bluetooth devices. Find "BluStreamFM" from the list, and select "Connect". Light flashes blue/red when in pairing mode and then solid blue when initial connection is made. Then flashes blue when device is paired and connected.

(No Pairing Code is Required)

Steps to add up to 4 additional devices: Disconnect any actively paired device. Control Button LED (B) will begin flashing blue/red, pair new device using above steps.

NEED TO CHARGE YOUR DEVICE AT THE SAME TIME? HERE'S HOW!



USB Charging Port

BluStream FM features a 5 volt 2.4A charging port which can be used to charge your smartphone, or other device (charging cable not included). Simply insert your USB charging cable into the charging port on the BT43IS Rev C.

CALLING INSTRUCTIONS




How to Make Calls Using Your BT431S Rev C

Make sure your phone is paired, and radio and transmitter are set to same channel to hear music and phone calls from your phone.

To dial a phone number use your phone's keypad or simply activate Voice Recognition by pressing and holding Control Button (B.)

See below chart for how to accept/answer and end calls.

Action	Description
ACCEPT/END CALLS	Press (B) control button once If using optional visor extended mic, use same steps as above for calling control with phone button.
REDIAL LAST CALL	Press (B) control button three times If using optional visor extended mic, use same steps as above for calling control with phone button.



HOW TO PLAY YOUR PHONE'S AUDIO

On your device, access your music/media player of choice. Adjust the volume using your device and radio volume, the audio will play through the channel selected.

CONTROL BUTTON FUNCTIONS

Action	Description
PLAY/PAUSE	Press button once
FORWARD TRACK	Press button twice
ACTIVATE VOICE RECOGNITION	Press button and hold

Adjust the volume using your device and radio volume.

CABLE MANAGEMENT



Step 1

Slide the back cover on module (A) up to remove it



Step 2

Remove the cable from under the tab and start winding clockwise around the center




Step 3

Tuck the cable back under the tab when you are finished and replace the back cover

ABOUT AUTO-CONNECT/SHUT-OFF

BT43IS Rev C will auto-connect after the first pairing.

BT43IS Rev C will auto shut-off after 5 minutes if not being used to conserve battery.



How to Reconnect with BT43IS Rev C

If the 12v port turns on/off with your ignition key, it will automatically turn on. But if the 12v port is constantly on, you will need to press the Control Button (B) to power up.

SAFETY WARNING

Please Read!

This equipment may be reset by unintentional electrostatic discharge during operation. Exposure to direct sunlight or extreme heat may cause damage or malfunction.

FCC Class B Radio Frequency Interference Statement: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, more of the following measures:

1. Re-orientate or relocate the receiving antenna.
2. Increase the separation between the equipment and receiver.
3. Connect the equipment into an outlet on a circuit different from that of which the receiver is connected.
4. Consult the dealer or an experienced radio / television technical for help.

NOTICE: The changes of modifications not expressly approved by the party responsible compliance could void the user authority to operate the equipment

Technical Support

US

AAMP Global
Tel: 866-788-4237
support@iSimple.com
www.iSimple.com

EU

AAMP Global UK
Tel: +01-800-477-2267
support@iSimple.com
www.iSimple.com

FCC WARNING

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

To maintain compliance with FCC's RF Exposure guidelines, This equipment should be installed and operated with minimum distance between 20cm the radiator your body: Use only the supplied antenna.

FCC RF exposure statement:

The equipment complies with FCC Radiation exposure limit set forth for uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.

FCC ID: XBD-BT43ISC



www.iSimple.com
facebook.com/isimplesolutions