



Get Roman! Get Voice!

R539

Bluetooth Headset

User Manual

ShenZhen Roman Technology co.ltd.

FCC ID: YGKR539

Overview

Thank you for choosing Roman brand. Roman Bluetooth headset with stylish, powerful, compatibility, allows you to experience the truly wireless phone calls, enjoy music. It is your best choice while in your office and outdoor activities.

Bluetooth wireless technology

Bluetooth wireless technology allows you to connect compatible communication device without cables. The Bluetooth connection does not need the phone and the headset to be in line of sight, but both devices should be within 10 meters (about 30 feet) from each other electronic devices.

There may be restrictions on using Bluetooth technology in some locations, Check with your local authorities or service providers.

1

output current should be: 100mA - 500mA). If charging voltage is too high, it is very likely to damage the Bluetooth headset.

Warning: Use the configured charger. Use other types of charges may violate the recognition of equipment or warranty, and could lead to danger. If there is a USB cable, it should be connected to the charger or computer which pass 3C certificate.

To recharge the battery

This headset adopts built-in non-removable rechargeable batteries. Please do not try to take out the batteries from the headset in order to avoid damage to the headsets. When the headset is not in use for a long time, please put it in a dry place with good ventilation, and recharge it every two months.

1. When connected headset flashes in red light, and there is beeps of low battery prompt in the receiver, it means the battery is low. In this case, if it continues to work it will power off automatically, then it needs to be recharged—insert the plug of the charger cable into headset jack.

8

2. Plug the charge to an AC socket
3. Red indicator lights when in charging. Before charging, please disconnect connection of charger and the headset and then plug it into headset again. It would take around 2 hours to be fully charged. After fully charged, red light will go off and blue light on, and disconnect the connection of charger and headset and power socket.
4. A fully charged headset can support up to 2-6 hours talk time and 100-180 hours standby time,(depends on headset model) While, the real talk time and standby time may be different because of different mobile phones, different use methods and different environment.

9

Get started

The headset contains the following parts

- 1) Indicating light (The light is red and blue)
- 2) MFB button
- 3) Volume button included + and -
- 4) Charging port. earphone port (Some of the headset, charging port and earphone have the same port)
- 5) Ear hook
- 6) Microphone port
- 7) Earpiece

Before you start using the headset, you must change it fully and connect the headset with a compatible phone or device

Note: Parts of the headset are magnetic, metallic material may be attracted to the headset. Do not place credit cards or other magnetic storage media near the headset, because information stored on them maybe erased.

2

Basic operation

Switch on Pairing: Press MFB button about 3 seconds until blue and red indicator light will be flashing 3 times together, and with voice prompt “power on”, then red and blue lights flashing alternatively with voice prompt “pairing”, pairing time for 150 seconds, if pairing timeout, the blue indicator light has been flashing until 6 minutes later will be power off.

Connecting: After pairing with the mobile phone successful, you will hear voice prompt “pairing successful”, after connect with the headset service successful, you will hear voice prompt “connected”from receiver.

End a call: When in talking time, click MFB button, you will hear a buzzer tone and with the voice prompt “end of the call”

Reject a call: When comes a call, press MFB button about 1 second until you hear a buzzer tone and with the voice prompt “reject the call”

3

Often problems and solutions

Problems description	Cause	Solution
Can not start	The power used up	Charge the battery fully before use
	Press MFB button too short	Re-start the headset
Can not charge	Plug is not placed well	Check the plug well
Can not turn off	Operate a wrongly made of the headset/software error	Plug to charger to reset
Can not find the headset	The headset is not searching status	Set the headset in a searching status
		Restore factory setting
when searching pairing devices	Mobile phone Bluetooth software error	Turn off the mobile phones and re-start

10

After sales service

Our company provides the guarantees in strict accordance with state regulations:

The warranty period is one year.

Our products do not provide unsalable goods refund,

Replacement services

When met problems when using, please contact local sales agent to deal with, for the following circumstances can not guaranteed free of charge.

- 1) Fragile label altered, tore;
- 2) Touched by liquid, damaged by water
- 3) Deformed seriously by outside force
- 4) Damage by wrongly operation or bad reserved
- 5) Damage caused by Accident or carelessness
- 6) Damage caused by commercial purpose and with non normal using conditions
- 7) Other situation similar to the above

11

Transfer a call: When in talking time, press MFB button for 1 second until you hear a buzzer tone

Answer a call: When comes a call, the voice prompt phone number, click MFB button, you will hear a buzzer tone

Redial the last number, when in a standby time, double click Volume+ button one time, you will hear a buzzer tone

Lost warning: beyond the connect distance will has the voice prompt “Connection interruption”with blue indicate light flashing.

Setting/Pause playing: Click MFB one time, repeat operation to pause playing.

Volume plus: Per click volume + button once, the receiver voice will increase 1 level, to increase the voice to largest until you hear a buzzer tone and with the voice prompt “the largest voice”

4

Volume decline: Per click volume - button once, the receiver voice will decline 1 level, to decline the voice to lowest until your hear a buzzer tone

Backward music: When playing music, press volume “-”button for1 second to get the previous song.

Forward music: Press volume + button for 1 second to get the next song.

Three-Way Call setting: When on call and a new call comes, short press MFB button one time, end the current Call (A), and receive the Call (B), press MFB button about 1 second, can refuse Call(B) to continue with Call (A). When on the phone and a new call comes; double click MFB button one time, can switch Call(A) and Call(B) two-way communication.

Power off: With headset in any state, press MFB button about 5 seconds, red and blue indicate light flashing 3 times with the voice prompt “power off”

5

Warm Tips

1. To extend the battery life, Roman recommends charging its headset at least once per month.
2. Use only Roman-approved charges, Unauthorized or Non-Roman charges could cause damage to the headset.
3. Use only a moderate volume setting necessary to hear your conversation or music.
4. Do not wear headset while sleeping, so as to avoid damage to the device and your hearing.
5. Do not use mobile phone while driving. Roman recommends using its headsets to ensure your safety
6. Keep your device and all accessories out of reach children. Some small parts may cause chocking or serious injury if swallowed.

12

Nationwide Warranty Card

Warranty Conditions

Our company’s warranty period is one year, if you found any problem when using, please contact your local dealer for timely after-sale deal.

The following situations are without warranty:

1. If no warranty card and valid invoice
2. Over the validity of warranty period
3. Damage caused due to improper use and maintenance
4. Non-authorized repairer had dismantled
5. The labeling information on the warranty card is inconsistent with the goods
6. Damage due to force majeure

Note: In accordance with the warranty card instructions, are under normal use, fault due to quality problems or caused by the product itself and in the warranty period, our company will be responsible for giving free warranty sevice

13

Voice prompt control: When connection standby mode, press MFB button for 1 second until you hear a buzzer prompt and let go. Repeat the operation again will close the voice prompt.

Multi-point function Operating: Using the paring way to connect with Phone A, and then turn off the headset. Then continued to use the paring way to connect with Phone B, and turn on the Phone A Bluetooth function, the Phone A will be connected with Bluetooth headset automatically (the phone should have the automatic return function) or click Bluetooth headset to connect Phone A by hand directly. Now the Bluetooth headset connect A and B two phones, realize one Bluetooth headset connect 2 phones function.

Headset photograph: When connection in ready mode, enter the camera interface, double click MFB button one time.

Open the keyboard or transfer to Bluetooth photograph after connected mobile phone: short press volume +/- together.

6

Switch in Chinese or English prompt: After the headset got into pairing mode, press volume -for 2 seconds

Battery prompt: Press volume +/- together for 2 seconds together.

Open and close the voice prompt: pairing mode, long press volume + until you hear the voice prompt.

Open and close the photograph function: when in pairing mode, long press MFB button, volume “+/-”button together for 5 seconds until you hear a buzzer prompt.

Clear the headset pairing history: Plug the charge, press MFB button and volume - button together for 3 seconds until you see the purple lights flashing one time.

Chargers and batteries

Before charging the headset please check if the specifications of the charger label is in accordance with the requirements(the charge output voltage should be: DC5V+/-0.25V;

7

Special announcement

1.Because of some Android phones manufactory made some changes for the original android system, it caused compatibility problems occur in some Android phones, for example, you can not use three side calls normally on Mi mobile phone.

2.When use photograph function, you need to get into mobile setting to set the volume control for photograph, if it still cans not realize control photograph, you can download “360 camera”APP install to you mobile phone.

3.After doing the test for few Android phones, after use headset photograph function, it will caused the input method will change to the system default input method, in this way, please reset to commonly use input method after disconnected.

14

4.Please double click the volume + button to redial the last number immediately once your paused music, there is about 10 seconds delay when pausing music of some phones itself, the operation is not useful, please operate after 10 seconds later or when in connection ready mode.

5.After testing, there are some of outdate Nokia and red Mi phones can not compatible with HID agreement, it will caused can not connection or can not take picture, please close the photograph function (The operation details please see the functions specification)

15

FCC Statement:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment to an outlet on a circuit different from that to which the receiver is connected.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: Modifications to this product will void the user's authority to operate this equipment.