

Bluetooth Mono Headset

User's Manual

Model: R6360 R5 R505 R510 R515
R520 R525 R535 R550 R565 R560
R570

FCC ID:YGKR6360

Charging the battery

Bluetooth has an internal, no removable, Li-Polymer rechargeable battery. Do not attempt to remove the battery from the device as you may damage the device. Please do not use the device while being charged.

1. For first time use, please fully charge the headset.
2. Connect the charger to a wall outlet and connects the charger cable to the charger socket.
3. While the charger is connected, the red indicator light is displayed during charging. Charging the battery fully may take up to 1 hour.
4. When the battery is fully charged, the red indicator light turns off and the blue indicators will solid light, please disconnect the

charger from the headset and the wall outlet.

5. The fully charged battery can keep the power up to 4 hours of talk-time. When the headset is powered on and battery power is low, the headset will emit reminder tones every 20 seconds in the earphone, and the indicator light will turn red.

Battery information

1. Your device is powered by a Li-Polymer chargeable battery. The full performance of a new battery is achieved only after two or three complete charge and discharge cycles. The battery can be charged and discharged hundreds of times, but it will eventually wear out.

2. Unplug the charger from the electrical plug and the device when not in use. Do not leave a fully charged battery connected to a charger, since overcharging may shorten its lifetime. If left unused, a fully charged battery will lose its charge over time.

It is recommended that you fully charge the headset before leaving it

unused for a long time. To prevent over discharge endangers the battery, you are recommended to fully charge the headset every 2 months.

Basic Operation

Before you use the headset for the first time, you must pair it with your Bluetooth[®] mobile phone or other Bluetooth[®] devices (The “Device”). In this user guide, we take mobile phone as the pairing object for example. Please pair according to the following steps:

- 1) Place the headset and the device within 1 meter distance area.
- 2) Ensure the headset is off, then press Multi-function Button for 5 seconds until the blue and red light flash alternately; the headset is on pairing mode now.
- 3) Activate your mobile's Bluetooth[®] functions by referring to your

mobile user guide

for details. Make the mobile to search for the Bluetooth[®] device.

4) Your mobile phone will find the headset and show it on the list.

5) Select the name, after press “OK” to confirm, input the password “0000” to finish pairing.

6) When the headset is paired with mobile phone, you will hear a beep and the blue indicator light will flash 5 times quickly, and then enter the standby state.

- 7)When the headset is in the pairing mode, if you didn't finish the pairing process within 2 minute, the headset will enter the standby state. If you want to pair again, you need to repeat the steps 1)-6).

8) If your master device is compliant to Bluetooth v2.1 specification, the headset may not ask password.

9) The headset supports multi-point technology, if you want to connect the headset to the second Bluetooth- enabled mobile, please repeat the pairing operation steps above. When complete pairing, turn off the headset and then turn on again, the headset will connect to both 2 mobiles automatically.

Wearing your headset

1. The headset is provided with an ear hook that you can use for a

better fit on your ear.

2. To use the headset without the ear hook, plug the headset into your ear and point the headset toward your mouth.

3. To use the headset with the ear hook, insert the ear hook into the small opening at the back of the headset.

4. The headset can be worn on either the left or right ear by changing the direction of the ear hook.

Turning headset on /off

Turning on the headset

When the headset is turned off, press and hold the MFB for about 2s, the headset will emit 2 beeps, and the blue indicator will flash at the same time, the headset is now on.

Connecting to a Bluetooth[®]-enabled mobile phone

If the headset has completed the pairing operation successfully, when the headset

turns on, it will connect to the phone(s) you last connected automatically. Please ensure your phone(s)'s Bluetooth[®] function is activated.

Turning off the headset

At any working state after the headset is powered on, press and hold MFB for about 4s, the headset will emit 2 beeps, and the red indicator will flash at the same time, the headset is powered off now.

Important:

When the headset has connected to 2 mobiles phones, it should be distinguished the connection sequence for some operations. As our definition, the phone first connected to headset is phone 1, the second one is phone 2.

If the headset is out of range, it will automatically try to reconnect the device for 5 times.

To conserve power, if the headset is not connected to a device in 1 hour, the

headset will turn off automatically.

Head-free function

Making a call-Using phone's keypad

In the stand-by mode, you can dial the number on your phone(s)'s keypad to make a call.

Use Voice-Dialing

In the stand-by mode, press MFB briefly, you will hear a short tone from the headset, and the phone will prompt you say the voice tag which you have already attached to your contact. If the voice tag is identified by the phone, the related number will be dialed. Please insure that your mobile phone supports this voice dialing function ,and voice tags have been set up on your mobile phone prior to attempting this. Please refer to your mobile phone's user guide or contact your service provider.

Important:

In a state of multi-connection is existed, the voice - dialing function is only available for phone 1.

Last number re-dialing

In the stand-by mode, double press MFB the last number you dialed will be re-dialed.

Important:

In a state of multi-connection is existed, the last number re-dialing function is only available for phone 1.

Answering a call

When you receive an incoming call, press the MFB shortly to answer the incoming call. You can also answer an incoming call directly from your phone's keypad.

Ending a call

When a call is in progress, press the MFB shortly. This will end the call. You can also end a call on your mobile phone(s) keypad.

Reject an incoming call

When you receive an incoming call, double press MFB to reject the incoming call.

Troubleshooting

If you can not connect the headset to the mobile phone, please try the following steps:

- 1) Ensure the headset is charged fully and it is paired with your mobile phone.
- 2) Ensure the headset is not connected with other Bluetooth[®] device.
- 3) Ensure your mobiles Bluetooth[®] feature is activated.
- 4) Ensure the headset is within a maximum of 10 meters of your mobile and there is no obstruction, such as walls or other electronic devices in between.

LED Indication

Headset status	LED Indication
Switch on	The purple indicator turns on and keeps on for 3 seconds

Paring state	The red and blue indicator flashes alternatively
In idle state after paired	The blue indicator flashes 1 time every 5 seconds
Incoming call	The purple indicator flashes
During call	The blue indicator flashes once every 8 seconds
Switch off	The red indicator flashes 3 times
Low battery	The red Led flashes

Charging	The red indicator keeps on
Charging finished	The blue indicator on

SPECIFICATION

Mono Bluetooth Headset

Bluetooth Version: V2.1+EDR

Mode: Hands Free/Headset

Frequency: 2.4GHz

Transmit Power: Class 2

Range: 10M

Power: AC Input 110-240V, DC Output 5V

Talking Time: 8H about

Standby Time: 160H about

Rechargeable 80mAh Li-Polymer Battery

*Operating Temperature: -10 °C ~ 50°C

*Storage Temperature: -20 °C ~ 60°C

Battery information

Your device is powered by a rechargeable battery. The full performance of a new battery is achieved only after two or three complete charge and discharge cycles. The battery can be charged and discharged hundreds of times, but it will eventually wear out.

Unplug the charger from the electrical plug and the device when not in use. Do not leave a fully charged battery connected to a charger, since overcharging may shorten its lifetime. If left unused, a fully charged battery will lose its charge over time.

Leaving the device in hot or cold places, such as in a closed car in summer or winter conditions, will reduce the capacity and lifetime of the battery. Always try to keep the battery between 15°C and 25°C (59°F and 77°F). A device with a hot or cold battery may not work temporarily, even when the battery is fully

charged. Battery performance is particularly limited in temperatures well below freezing.

Do not dispose of batteries in a fire as they may explode. Batteries may also explode if damaged. Dispose of batteries according to local regulations. Please recycle when possible. Do not dispose as household waste.

Care and maintenance

- Keep all accessories and enhancements out of the reach of small children.
- Keep the device dry. Precipitation, humidity, and all types of liquids or moisture can contain minerals that will corrode electronic circuits. If your device does get wet, allow it to dry completely.
- Do not use or store the device in dusty, dirty areas. Its moving parts and electronic components can be damaged.
- Do not store the device in hot areas. High temperatures can shorten the life of electronic devices, damage batteries, and warp or melt certain plastics.

- Do not store the device in cold areas. When the device returns to its normal temperature, moisture can form inside the device and damage electronic circuit boards.
- Do not drop, knock, or shake the device. Rough handling can break internal circuit boards and fine mechanics.
- Do not use harsh chemicals, cleaning solvents, or strong detergents to clean the device.
- Do not paint the device. Paint can clog the moving parts and prevent proper operation.

All of the above suggestions apply equally to your device, battery, charger, or any enhancement. If any device is not working properly, take it to the nearest authorized service facility.

IMPORTANT REGULATORY INFORMATION

This device complies with Part 15 of the FCC Rules: Operation is subject to the following conditions:

1. This device may not cause harmful interference and
2. This device must accept any interference that is received, including any interference that may cause undesired operation.

WARNING:

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.