



User Manual

Model:S530
FCC ID:YGKS530

ShenZhen Roman Technology co.ltd.

Introduction
Thank you for choosing Roman brand, Roman Bluetooth headset with stylish, powerful, compatibility, allows you to experience the truly wireless phone calls and enjoy music. It is your best choice while in your office, driving and outdoor activities.

Bluetooth wireless technology
Bluetooth wireless technology allows you to connect compatible communication devices without cables. The Bluetooth connection does not need the phone and the headset to be in line of sight, but both devices should be

within 10 meters (about 30 feet) from each other. Connections can be subjected to interference from obstructions, such as walls or other electronic devices.
The headset is compliant with the Bluetooth version V4.0/V3.0/2.1+EDR (Enhanced Data Rate), and supports the following profiles: Headset Profile 1.1/1.2 and Hands-free profile 1.5/1.6, A2DP/AVRCP. Check with the manufacturers of other devices to determine whether the device is compatible with the headset.
There may be restrictions on using Bluetooth technology in some locations. Check with your local authorities or service providers.

Get started
The headset contains the following parts (vary depending on the specific model) :
1. Indicating light(The light is red,green or blue);
2. MFB button(With telephone or power logo);
3. Volume button included + and - (Some of the headset does not support);
4. Charging port, earphone port(Some of the headset, charging port and earphone have the same port);
5. Ear hook;
6. Microphone port;
7. Earpiece;(Some of the headset, the ear pad can be

interchangeable with Large, Medium, Small size);
8. LCD display;(Some of the headset support)
9. Vibrate;(Some of the headset support)
10. Buzzer;(Some of the headset support)
Before you start using the headset, you must charge it fully and connect the headset with a compatible phone or device.
Note: Parts of the headset are magnetic, metallic material may be attracted to the headset. Do not place credit cards or other magnetic storage media near the headset, because information stored on them maybe erased.
Roman Mono series headset support functions: making and

receiving a call
Roman Stereo series headset support functions: making and receiving a call/listening to music/music control (previous and next song)/Play and Pause/MP3

Basic operation
(**Note: short press is to click the button once, twice press is to press the button twice as fast; long press is to hold and press the button more than one second**)
Switch on Pairing:
1、 In the off state, long press and hold the MFB button until the blue light or red and blue lights flashing alternately

then release the button (here with buzzer or voice tone), it means that the headset enters into pairing mode.
2、 In the off state, press the MFB button, when you see the blue light flashing, or hear the voice prompted "power on pairing" , then the headset enters into pairing mode automatically.
Connecting: Turn on your mobile phone's Bluetooth to search for the Bluetooth headset, find the model number, then please choose and confirm it and input password 0000 if needed(if the Bluetooth version is V2.1 or higher, no need to input the password), choose headset service to connect successfully.

Answer a call: when comes a call, some headsets have the TONE/Vibration/ buzzer tone/voice prompt/telephone number prompt, just press the MFB key shortly to enter Talking mode when hearing the buzzer tone.
Reject a call: when comes a call, long press the MFB key/ Volume +/ Volume - and release your hand until you hear a buzzer tone/voice prompt, then it will reject the call.
End a call: when in talking mode, press the MFB key shortly to end the call.
Volume Control: If your headset have volume control, when talking, short press the volume+ to increase the volume, short

press volume- to decrease the volume.
Forward/backward Music control: when playing music by using stereo Bluetooth headset, press the volume sign (+)for 5 to 10sec to get the next song, press the volume sign(-) to get the previous song.
Pause playing: when playing music by using stereo Bluetooth headset, shortly press the MFB key to pause playing, shortly press the MFB again to go on playing.
Setting music: If connected successfully, most mobile phone

automatically support playing music by using Bluetooth headset, but some mobile phone need to set it: when playing music, please choose Bluetooth A2DP service to play music. For more details, please refer to the User Manual of your mobile phone.
Talking Switcher: when talking using Bluetooth headset, keep pressing the MFB twice or long press to switch to the mobile phone, repeat the above operation to go on talking with the Bluetooth headset.
Re-dial last number: when in a standby mode, press the MFB key longer or shortly press it twice to redial the last call.

Voice Dialing: when in a standby mode, keep pressing the MFB twice to operate the voice dialing on the mobile phone, enabled voice control. Then again keep pressing MFB twice to cancel it. (This function should be supported by mobile phone)
Multi-point Function Operating:
1、 Using the pairing way to connect with Phone A, then turn off the headset. Then continued to use the pairing way to connect with Phone B, and turn off the headset again. At last, turn on the headset, do not enter into pairing mode, the headset can connect with Phone A and Phone B automatically. Now the headset can receive the call from

Phone A and Phone B.
2、 Using the pairing way to connect with Phone A, then turn off the Phone A Bluetooth function and turn off the headset as the same. Then continued to use the pairing way to connect with Phone B, and turn on the Phone A Bluetooth function, the Phone A will be connected with headset automatically. (The phone should have the automatic return function)
Pairing way details as below:
1. Press and hold MFB until the indicator light turns on in blue

or red and blue lights flashing alternately.
2. Activate the Bluetooth feature on the Phone A, and set the phone to search for Bluetooth devices.
3. Select the headset from the list of found devices.
4. Enter passcode "0000" if prompted by the phone. If the headset pairs correctly you will hear a beep and the blue indicator light will flash, in some phones you may need to make the connection separately after pairing.
5. Turn off your headset.
6. Turn on your headset again.
7. Activate the Bluetooth feature on another Phone B and set the phone to search for Bluetooth device. Enter passcode

"0000" if prompted by the phone. If the headset pairs correctly you will hear a beep and the blue indicator light will flash, in some phones you may need to make the connection separately after pairing.
8. Turn off the headset again.
9. Turn on the headset; do not enter into pairing mode. Then you will find it connects the two mobiles successfully.
Three-Way Call Setting:
1、 When on call and a new call comes, press MFB button once, end the current Call (A), and receive the Call (B); Long press MFB button 3 seconds, can reject Call (B) to continue with Call (A) if you do not want to answer Call (B).

When on the phone and a new call comes; press MFB button twice again, can switch Call (A) and Call (B) two-way communication.
Enter into three-way calling, short press MFB once, end the current call, and recover the call on hold. (Some of the headset cannot support)
2、 When on call and a new call comes, press MFB button once to end the current Call (A), receive the call from Call (B); long press MFB 1 second to hold on the current Call (A) and receive Call (B). Press MFB button 1 second again, then recover to Call (A). (Some of the headset cannot support)

Restore Headset Factory Parameter Setting:
The following steps can recover headset parameter setting.
1. Pairing status ----The Blue indicator light or the Blue and Red indicators light alternatively, press MFB for 2 seconds then release it, the Blue and Red indicators will be flashing at the same time.
2. When the headset is in charging mode, press volume up or volume down until the Blue indicator flash three times.
3. When the headset is in charging mode, press MFB until the Blue or Red indicator flash.

MP3 Mode:
When the headset is in standby mode, press MP3 mode button or long press Play/Pause button, then enters into MP3 mode.
Turn Off The Headset:
When the headset is working, long press MFB button until the Blue or Red indicator flash at the same time (with buzzer/voice prompt), then the headset turns off.

Chargers and batteries
Before charging the headset please check if the specifications of the charger label is in accordance with the requirements (the charger output voltage should be: DC5V + / - 0.25 V; output current should be: 100mA - 500mA). If charging voltage is too high it is very likely to damage the Bluetooth headset.
Warning: Use the configured charger. Use other types of chargers may violate the recognition of equipment or warranty, and could lead to danger. If there is a USB cable, it should be connected to the charger or computer which pass 3C certificate.

To recharge the battery
This headset adopts built-in non-removable rechargeable batteries. Please do not try to take out the batteries from the headset in order to avoid damage to the headsets. When the headset is not in use for a long time, please put it in a dry place with good ventilation, and recharge it every two months.
1. When connected headset flashes in red light, and there is beeps of low battery prompt in the receiver, it means the battery is low. In this case, if it continues to work it will power off automatically. Then it needs to be recharged---insert the plug of the charger cable into headset jack.

2. Plug the charger to an AC socket.
3. Red indicator lights when in charging. Before charging, please disconnect connection of charger and the headset and then plug it into headset again. It would take around 2 hours to be fully charged. After fully charged, red light will go off and blue light on, and disconnect the connection of charger and headset and power socket.
4. A fully charged headset can support up to 2-6 hours talk time and 100-180 hours standby time. (depends on headset model) While, the real talk time and standby time may be different because of different mobile phones, different use methods and different environment.

Often problems and solutions

Problems description	Cause	Solution
Can not start	The power used up	Charge the battery fully before use
	Press MFB button too short	Press the MFB button for 3 seconds to re-start the headset
Can not charge	Plug is not placed well	Check the Plug well

Can not turn off	Operate a wrongly made of the headset/software error	Plug to charger to reset
Can not find the headset when searching pairing devices	The headset is not in searching status	Set the headset in a searching status
	Mobile phone Bluetooth software error	Turn off the mobile phones and re-start.

After sales service
Our company provides the guarantees in strict accordance with state regulations:
The warranty period is one year.
Our products do not provide unsalable goods refund, replacement services.
When met problems when using, please contact local sales agent to deal with, for the following circumstances can not guaranteed free of charge.
1. Fragile label altered, tore;
2. Touched by liquid, damaged by water
3. Deformed seriously by outside force

4. Damage by wrongly operation or bad reserved
5. Damage caused by Accident or carelessness
6. Damage caused by commercial purpose and with non normal using conditions
7. Other situation similar to the above
Warm Tips
1.To extend the battery life, Roman recommends charging its headset at least once per month.
2. Use only Roman-approved chargers, Unauthorised or Non-Roman chargers could cause damage to the headset.

3. Use only a moderate volume setting necessary to hear your conversation or music.
4. Do not wear headset while sleeping, so as to avoid damage to the device and your hearing.
5. Do not use mobile phone while driving. Roman recommends using its headsets to ensure your safety.
6. Keep your device and all accessories out of reach children. Some small parts may cause choking or serious injury if swallowed.

Nationwide Warranty Card (For Buyer Reserve)
Warranty Conditions
Our company's warranty period is one year, if you found any problem when using, please contact your local dealer for timely after-sale deal.
The following situations are without warranty:
1. If no warranty card and valid invoice
2. Over the validity of warranty period
3. Damage caused due to improper use and maintenance
4. Non-authorized repairer had dismantled
5. The labeling information on the warranty card is inconsistent with the goods
6. Damage due to force majeure

Nationwide Warranty Card (For Seller Reserve)
Warranty Conditions
Our company's warranty period is one year, if you found any problem when using, please contact your local dealer for timely after-sale deal.
The following situations are without warranty:
1. If no warranty card and valid invoice
2. Over the validity of warranty period
3. Damage caused due to improper use and maintenance
4. Non-authorized repairer had dismantled
5. The labeling information on the warranty card is inconsistent with the goods
6. Damage due to force majeure

Note: In accordance with the warranty card instructions, are under normal use, fault due to quality problems or caused by the product itself and in the warranty period, our company will be responsible for giving free warranty service.

Customer Name: _____
Contact number: _____
Address: _____
Product Type: _____
Purchase Date: Year Month Day
Invoice Number: _____
Maintenance records: _____

Note: In accordance with the warranty card instructions, are under normal use, fault due to quality problems or caused by the product itself and in the warranty period, our company will be responsible for giving free warranty service.

Customer Name: _____
Contact number: _____
Address: _____
Product Type: _____
Purchase Date: Year Month Day
Invoice Number: _____
Maintenance records: _____

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.