

Product Description

Version: Bluetooth V4.1 Charging method: Power supply with output of DC 5V 135mA


Battery type: Rechargeable lithium-ion polymer battery Bluetooth power class: Class 2 Profile supported: HSP/HFP/A2DP/AVRCP

Talk time: Up to 10 hours Listen time: Up to 10 hours Standby time: 180 hours

Play audio file from a mobile phone. laptop or other Bluetooth device connected with it.(AV dongle : General BT dongle)

Play audio from a PC after connected with its BT dongle, and also support wireless internet voice chat through QQ, WECHAT and SKYPE.

Headset Overview



Pairing Steps

Press and hold 5s



NOTE: The headset will power off automatically 3 minutes without connection.

Under power-off status, press and hold the MFB untill the indicator light flashes red and blue alternatively, then the Headset enters the pairing mode;

Turn on Bluetooth on your moblie, find the Model No. of the Headset, and connect. Turn off Bluetooth of the first mobile, and repeat the step above to connect with the second mobile.

Pairing Steps

Power on/off o





Power on - Press and hold the multi-funcation button (MFB) for 2s untill the BLUE light flashes:

Power off- Press and holde the MFB for 5s untill the RED light on for 2s;

Call answer



Call answer - Answer by your phone or press the MFB.

正面

反面

Accessorise:

- * Instruction x 1pcs
- * Extra ear gels x 2pcs

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and

(2) this device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications to this unit not expressly approved by the party

responsible for compliance could void the user's authority to operate the equipment NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation

If this equipment does cause harmful interference to radio or television recention. which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.



Voice Prompt

- Power on/off o
- # You will hear "power on" when the Headset is power on.
- # You will hear "power on" when the Headset is power off.
- # You will hear "connected" when the Headset is paired.
- # You will hear "low battery" when the Headset is in low power status.

Warning:

.Use and keep the Headset under ambieent temperatures;

- Don't throw it in case product damage caused:
- Don't disassemble, repair or alter the Headset;
- Don't clean the Headset with chemical
- . Use a USB charger of DC5V to charge the Headset if necessary;
- Don't discard the Headset at randon, or put it into fire or high temperature environment (60/140) in case of danger.

Track Control₩



Track control - Press and hold the "Voleme+" button for 2s to skip to the next song; Press and hold the "Volume -"button for 2s to play the previous song.

Volume Adjust ◄



Volume adjust - Press the "Volume +" or "Volume -" button to increase or decrese the volume.

Last Number Redial



Last number redial - Quicky tap the MFB twice to redial the last dialed phone number:

Play Music 🎵



Play music - Press the MFB to play/pause music under music playing status.

Call End 👨



Call end - End by your phone or press the MFB;

Call Reject 🐪



Call reject - Reject by your phone or press and hold the MFB for 2s